arXiv:cs/0602054v1 [cs.IT] 15 Feb 2006

Explicit Space-Time Codes Achieving The Diversity-Multiplexing Gain Tradeoff

Petros Elia, K. Raj Kumar, Sameer A. Pawar
P. Vijay Kumar and Hsiao-feng Lu

***Abstract*— A recent result of Zheng and Tse states that over a quasi-static channel, there exists a fundamental tradeoff, referred to as the diversity-multiplexing gain (D-MG) tradeoff, between the spatial multiplexing gain and the diversity gain that can be simultaneously achieved by a space-time (ST) block code. This tradeoff is precisely known in the case of i.i.d. Rayleigh-fading, for $T \geq n_t + n_r - 1$ where T is the number of time slots over which coding takes place and n_t, n_r are the number of transmit and receive antennas respectively. For $T < n_t + n_r - 1$, only upper and lower bounds on the D-MG tradeoff are available.**

In this paper, we present a complete solution to the problem of explicitly constructing D-MG optimal ST codes, i.e., codes that achieve the D-MG tradeoff for any number of receive antennas. We do this by showing that for the square minimum-delay case when $T = n_t = n$, cyclic-division-algebra (CDA) based ST codes having the non-vanishing determinant property are D-MG optimal. While constructions of such codes were previously known for restricted values of n, we provide here a construction for such codes that is valid for all n.

For the rectangular, $T > n_t$ case, we present two general techniques for building D-MG-optimal rectangular ST codes from their square counterparts. A byproduct of our results establishes that the D-MG tradeoff for all $T \geq n_t$ is the same as that previously known to hold for $T \geq n_t + n_r - 1$.

***Index Terms*— diversity-multiplexing gain tradeoff, space-time codes, explicit construction, cyclic division algebra.**

I. INTRODUCTION

Consider the quasi-static, Rayleigh fading, space-time (ST) MIMO channel with quasi-static interval T, n_t transmit and n_r receive antennas. The $(n_r \times T)$ received signal matrix Y is given by

$$Y \;=\; \theta H X + W \tag{1}$$

where X is a $(n_t \times T)$ code matrix drawn from a ST code $\mathcal{X}$, H the $(n_r \times n_t)$ channel matrix and W represents additive noise. The entries of H and W are assumed to be i.i.d., circularly symmetric, complex Gaussian $\mathbb{C}\mathcal{N}(0,1)$ random variables. The real scalar θ ensures that the energy constraint

$$\theta^2 ||X||_F^2 \;\leq\; T\ \text{SNR}, \quad \text{all } X \in \mathcal{X}, \tag{2}$$

is met. We set

$$\mathcal{Z} \;=\; \{\theta X \mid X \in \mathcal{X}\}$$

and will refer to $\mathcal{X}, \mathcal{Z}$ as the unnormalized and normalized ST codes [1] respectively.

Multiple transmit and receive antennas have the potential of increasing reliability of communication as well as permitting communication at higher rates. These aspects are quantified by the diversity and spatial multiplexing gains respectively. In a recent landmark paper, Zheng and Tse [1] showed that there is a fundamental tradeoff explained below, between diversity and multiplexing gain, referred to as the diversity-multiplexing gain (D-MG) tradeoff.

The ergodic capacity [2], [3], i.e., capacity averaged over all realizations H of the space-time channel model in (1) is given by

$$C \;=\; \mathbb{E}\{\log\det(I + \frac{\text{SNR}}{n_t} H H^\dagger)\},$$

which for large SNR has the approximation

$$C \;\approx\; \min\{n_t, n_r\} \log(\text{SNR}). \tag{3}$$

The space-time code $\mathcal{X}$ transmits

$$R \;=\; \frac{1}{T} \log(\mid \mathcal{X} \mid)$$

bits per channel use. Let r be the normalized rate given by $R = r\log(\text{SNR})$. Following [1], we will refer to r as the (spatial) multiplexing gain [4]. From (3), it is seen that the maximum achievable multiplexing gain equals $r = \min\{n_t, n_r\}$. Let the diversity gain $d(r)$ corresponding to transmission at normalized rate r be defined by

$$d(r) \;=\; -\lim_{\text{SNR}\to\infty} \frac{\log(P_e)}{\log(\text{SNR})},$$

where P_e denotes the probability of codeword error. We will follow the exponential equality notation of [1] under which this relationship can equivalently be expressed by

$$P_e \doteq \text{SNR}^{-d(r)}.$$

A principal result in [1] is the proof that for a fixed integer multiplexing gain r, and $T \geq n_t + n_r - 1$, the maximum achievable diversity gain $d(r)$ is governed by

$$d(r) \;=\; (n_t - r)(n_r - r). \tag{4}$$

Petros Elia and P. Vijay Kumar are with the Department of EE-Systems, University of Southern California, Los Angeles, CA 90089 ({`elia,vijayk`}`@usc.edu`). K. Raj Kumar and Sameer A. Pawar are with the Department of Electrical Communication Engineering of the Indian Institute of Science, Bangalore, 560 012 ({`raj,sameerp`}`@ece.iisc.ernet.in`). This work was carried out while P. Vijay Kumar was on leave of absence at the Indian Institute of Science, Bangalore. Hsiao-feng (Francis) Lu is with the Dept. of Comm. Engineering, National Chung-cheng University, 160 San-Hsing, Min-Hsiung, Chia-Yi 621, Taiwan, R.O.C. (`francis@ccu.edu.tw`).

This research is supported in part by NSF-ITR CCR-0326628, in part by the DRDO-IISc Program on Advanced Research in Mathematical Engineering and in part from Grant NSC 93-2218-E-194-012.

[1] As pointed out by the reviewers, the collection of matrices $\mathcal{X}$ could also be regarded as forming a signal constellation in which case the term ST modulation might be more appropriate. However, we have retained the ST code label here to be in keeping with the widespread usage of this terminology in the literature.

The value of $d(r)$ for non-integral values of r is obtained through straight-line interpolation. For $T < n_t + n_r - 1$ only upper and lower bounds on the maximum possible $d(r)$ are available. The plots in Fig. 1 are for the case of $n_r = n_t = T = 4$. The two lines show upper and lower bounds on the best possible D-MG tradeoff achievable when $T = 4$ with any signalling scheme.



Fig. 1. *Upper and Lower Bounds on the D-MG Tradeoff in the case of* 4 *transmit and* 4 *receive antennas.*

Zheng and Tse [1] establish that the D-MG tradeoff curve coincides with the plot of outage probability and that random Gaussian codes achieve the D-MG tradeoff provided $T \geq n_t + n_r - 1$. They also show that orthogonal space-time block codes in general, achieve maximum diversity gain but cannot achieve maximal multiplexing gain. The reverse is shown to hold in the case of the vertical Bell-Labs layered space-time architecture (V-BLAST). Diagonal-BLAST (D-BLAST) in conjunction with MMSE decoding, is shown to achieve the tradeoff provided one ignores the overhead due to non-transmission in certain space-time slots. It is observed in their paper, that apart from the Alamouti [21] scheme that achieves the D-MG tradeoff in the case of a single receive antenna, there is no explicitly constructed coding scheme that achieves the optimum tradeoff for all $r > 0$.

A. *Prior work*

In this paper, we shall refer to a ST code that achieves the upper-bound on the D-MG tradeoff as being a D-MG optimal ST code, or more simply, an optimal code. The results in [1] spurred considerable research activity towards the construction of optimal codes and some of this is briefly reviewed below.

1) Case of Two Transmit Antennas: For M even, let $\mathcal{A}_{\text{QAM}}$ denote the M^2-QAM constellation given by

$$\mathcal{A}_{\text{QAM}} = \{a + \imath b \ \mid \ |a|, |b| \leq M-1, \ a, b \text{ odd}\}. \tag{5}$$

The literature includes several constructions of (2×2) ST codes that achieve the D-MG tradeoff. The unnormalized ST code matrices X in the constructions in [5]–[8] share a common structure, namely

$$X = \begin{bmatrix} x_1 & y_2 \\ y_1 & x_2 \end{bmatrix}$$

where the diagonal and anti-diagonal “threads” are unitary transformations of vectors with QAM components, i.e., where

$$\begin{bmatrix} x_1 \\ x_2 \end{bmatrix} = S_1 \underline{u}, \quad \begin{bmatrix} y_1 \\ y_2 \end{bmatrix} = S_2 \underline{v}$$

with $\underline{u}, \underline{v} \in \mathcal{A}_{QAM}^2$ and where S_1, S_2 are unitary. Setting $M^2 = \text{SNR}^{\frac{r}{2}}$ allows the ST code to transmit at information rate $R = r \log(\text{SNR})$ bits per channel use. The constructions differ on the selection of the particular unitary matrices.

In the Yao-Wornell papers, [5], [6] it is shown that by optimizing amongst the class of unitary matrices corresponding to rotation of vectors in the complex plane, the minimum determinant of the difference of two space-time code matrices exceeds $\frac{1}{2\sqrt{5}}$ independent of M and hence of the SNR. This is then used to show that this code achieves the upper bound on optimum D-MG tradeoff. This construction is the first to provide an explicit construction for a code that achieves the D-MG tradeoff for very value of n_t, n_r.

The construction by Dayal and Varanasi, [7] draws on earlier constructions by Damen et al [13] and El Gamal and Damen [14]. Here the authors optimize the coding gain through appropriate selection of the matrices S_1, S_2. As with the Yao-Wornell construction, the minimum determinant is bounded away from zero as $M^2 \to \infty$. While the D-MG tradeoff is not explicitly discussed in [7], by arguing as in [5], [6], the optimality of the Dayal-Varanasi construction can be established. The coding gain of the Dayal-Varanasi construction, especially relevant for lower values of SNR, is shown to improve upon that of the Yao-Wornell code.

A third construction of a ST code with $n_t = T = 2$ that achieves the D-MG tradeoff is the Golden code construction of Belfiore et al. [8], so called because of the appearance of the Golden number $\zeta = \frac{1+\sqrt{5}}{2}$ in the construction. The Golden code is an example of a class of codes known as perfect codes [11], [12] and this class of codes is discussed in greater detail below. Optimality of the Golden code construction is pointed out in [9]. Reference [12] contains other examples of (2×2) D-MG optimal codes as well.

A different thread-based construction of D-MG optimal (2×2) code can found in the paper by Liao et al. [10].

2) LAST Codes: In [15], El Gamal, Caire and Damen consider a lattice-based construction of space-time block codes and call these codes LAST codes. In this construction, a code matrix X in the space-time code $\mathcal{C}$ is identified with a $(n_t T \times 1)$ vector $\underline{x}$ obtained by vertically stacking the columns of the space-time code matrix. The construction calls for a lattice Λ_c and a sublattice Λ_s. Message symbols are mapped onto coset representatives $\{\underline{c}\}$ of the subgroup Λ_s of Λ_c that lie within the fundamental region $\mathcal{V}_s$ of the sublattice Λ_s. Thus the fundamental region of the sublattice serves as a shaping region for the lattice. The transmitted vector $\underline{x}$ is then given by

$$\underline{x} = \underline{c} - \underline{u} \pmod{\Lambda_s},$$

where $\underline{u}$ is a pseudorandom “dither” vector chosen with uniform probability from $\mathcal{V}_s$. The dither is assumed to also be known to the receiver. The lattice pair Λ_s, Λ_c, $\Lambda_s \subseteq \Lambda_c$ is drawn from an ensemble of lattices having good “covering” properties, an example of which can be found in a paper by Loeliger [16]. It is shown that this ensemble of lattices contains a lattice such that the resultant space-time code, when suitably decoded using generalized minimum Euclidean distance lattice decoding, achieves the D-MG tradeoff for all $T \geq n_t+n_r-1$. In actual code construction, a lattice drawn at random from the ensemble of lattices is used. A principal advantage of LAST codes is that in comparison to random Gaussian codes, the decoding is simpler and does not require searching over the entire codebook.

3) Division Algebra- Based Constructions:

a) ST Codes from Division Algebras: Space-time code construction from division algebras was first proposed by Sethuraman and Rajan [17]–[20] and independently shortly after, by Belfiore and Rekaya [22].

In [20], Sethuraman et al. consider the construction of ST codes from field extensions as well as division algebras (DA). Two methods of constructing ST codes from DA are presented. It is shown how Alamouti's code [21] arises as a special instance of these constructions. A general principle for constructing CDAs using transcendental elements is given and the capacity of the space-time block codes (STBCs) obtained via this construction studied. A second family of CDAs discovered by Brauer is discussed and applied to construct ST codes.

b) Non-Vanishing Determinant: The notion of a non-vanishing determinant (NVD) was introduced by Belfiore and Rekaya [22]. The coding gain of a space-time code as determined by pairwise error probability considerations, is a function of the determinant of the difference code matrix. It is therefore of interest to maximize the value of this determinant. The authors of [22] note that while many constructions of space-time codes have the property of having a non-zero determinant, this determinant often vanishes as the SNR increases and the size of the signal constellation is accordingly increased to provide increased spectral efficiency. In [22], the authors describe an approach for constructing CDA-based square ST codes whose determinant is bounded from below for all SNR and hence does not vanish. NVD code constructions are outlined for $n_t = T = 2^k$ and $n_t = T = 3 \cdot 2^k$. Example constructions are provided for $n_t = T = 2, 3, 4$.

c) Perfect Codes: In [12], Oggier et al. define a square $(n \times n)$ STBC to be a perfect code [2] if

- the code is a full-rate, linear-dispersion [47] code using n^2 information symbols drawn from either a QAM or HEX constellation,
- the minimum determinant of the code is bounded away from zero even as $M \to \infty$,
- the $2M^2$dimensional real lattice generated by the vectorized codewords, is either $\mathbb{Z}^{2M^2}$ or $A_2^{M^2}$ (A_2 is the hexagonal lattice), and
- each symbol X_{ij} in the code matrix has the same value of average energy.

Perfect codes have been shown through simulation, to have excellent performance as judged by codeword error probability. The authors of [12] show the existence of perfect CDA-based space-time codes for dimensions $n = 2, 3, 4, 6$. The Golden code is an example of a perfect code in 2 dimensions. More recently, Elia et al. [23] show how the perfect code construction can be generalized to yield perfect codes for any value of the integer n.

d) Constructions with NVD: In [24], square ST codes with the NVD property are constructed by Kiran and Sundar Rajan for $n_t = T = 2^k,\ 3{\cdot}2^k,\ 2.{\cdot}3^k$ or $n_t = T = q^k(q-1)/2$, where $q = 4s + 3$ is a prime. Also contained in this paper, is a lemma that simplifies the task of identifying the non-norm element γ needed in the construction of a CDA having a number field as its maximal subfield.

e) Approximate Universality: In [25], [26], Tavildar and Viswanath consider the correlated fading channel model in which the entries h_{ij} of the matrix H are allowed to have arbitrary fading distributions. They show the existence of permutation codes (codes based on permutations of the QAM constellation) that achieve the D-MG tradeoff in the case of the parallel channel (channel where H is diagonal). They note that by using D-BLAST in conjunction with a permutation code designed for the parallel channel, one can achieve the D-MG tradeoff of the general correlated fading channel in the limit as the delay parameter $T \to \infty$. The main result is a sufficient condition for a ST code to be approximately universal i.e., be D-MG optimal for every correlated MIMO fading channel. This sufficient condition is expressed in terms of the product of the squared-singular values of the difference code matrix. It is also shown that in the case of the i.i.d. Rayleigh fading channel, V-BLAST with a QAM signal constellation achieves the last segment of the D-MG tradeoff curve while D-BLAST achieves the first segment when $n_r = 2$.

After the initial submission of the present paper, a more detailed version [27] of [25], [26] containing proofs of all results, has appeared in preprint form. It is shown in this version (see also [28]) that the space-time block codes of Yao-Wornell as well as those presented in the original submission of our present paper here are approximately universal.

f) Other Work: Other references relating to the construction of space-time codes from division algebras include [31], [32], [46]. Some analysis of the D-MG tradeoff of some known constructions can be found in [9], [29], [30]. The rank-distance construction of Lu and Kumar [33] as well as subsequent generalizations in [34]–[36] are all optimal with respect to a different tradeoff known as the rate-diversity tradeoff which is based on the situation in which the signal constellation is fixed independent of SNR, and where pairwise error probability is used as a measure of performance.

B. Principal Results

A complete solution to the problem of explicitly constructing ST codes that achieve the D-MG tradeoff of the i.i.d. Rayleigh MIMO channel is presented in this paper.

The solution is presented in two parts. The first part establishes the optimality of a class of CDA-based ST codes having the non-vanishing determinant (NVD) property. The codeword matrices in this class of ST code are square i.e.,

---

[2] The results of the present paper establish that perfect codes are D-MG optimal as well.

$T = n_t$ and correspond to minimum-delay ST codes. Prior constructions [8], [11], [24] of such ST codes were restrictive in terms of the values of n_t that could be accommodated. In the present paper, a general construction for minimal-delay CDA based ST codes is given for all values of n_t.

In the second part, optimal ST constructions are provided for the rectangular, i.e., $T > n_t$ case. Both the square and rectangular constructions achieve the same tradeoff as do the constructions in the $T \geq n_t + n_r - 1$ case for which the D-MG tradeoff is exactly known from [1]. This not only establishes the optimality of the rectangular constructions, it also extends the range of values of T for which the D-MG tradeoff is exactly known from $T \geq n_t + n_r - 1$ to $T \geq n_t$.

C. Outline

The optimality of CDA-based ST codes having the NVD property is established in Section II. This section also provides some background on division algebras and on ST code construction from division algebras. Two constructions of optimal CDA-based ST codes, valid for all $n_t, n_r,\ T = n_t$ are then presented in Section III. Section IV also presents two constructions, but of optimal rectangular space-time codes valid for all $n_t, n_r,\ T > n_t$. Appendix I presents a primer on the relevant number theory. While the discussion in the paper is focused on constellations derived from an underlying QAM constellation, the construction techniques and optimality results also carry over to the case of the HEX constellation and this is discussed in Appendix II. Appendix III contains proofs not found elsewhere.

II. OPTIMALITY OF CDA-BASED ST CODES WITH NVD PROPERTY

A. Division Algebras

Division algebras are rings with identity in which every nonzero element has a multiplicative inverse. As commutative division algebras are fields, it is the non-commutativity of a division algebra that serves to differentiate them from fields and as it turns out, endows certain associated space-time codes with a key non-vanishing determinant property.

The center $\mathbb{F}$ of any division algebra D, i.e., the subset comprising of all elements in D that commute with every element of D, is a field. The division algebra is a vector space over the center $\mathbb{F}$ of dimension n^2 for some integer n. A field $\mathbb{L}$ such that $\mathbb{F} \subset \mathbb{L} \subset D$ and such that no subfield of D contains $\mathbb{L}$ is called a *maximal subfield* of D (Fig. 2). Every division algebra is also a vector space over a maximal subfield and the dimension of this vector space is the same for all maximal subfields and equal to n. This common dimension n is known as the *index* of the division algebra. We will be interested only in the case when the index is finite.

Example *1 (Quaternion Division Algebra):* The classical example of a division algebra is Hamilton's ring $D = \mathbb{R}(e, i, j, k)$ of quaternions over the real numbers $\mathbb{R}$, where e is the identity element and i, j, k are elements satisfying

$$i^2 = j^2 = k^2 = -1$$
$$ij = -ji = k, \qquad jk = -kj = i, \qquad ki = -ik = j.$$

The center of D is the field of real numbers $\mathbb{R}$ and one maximal subfield is isomorphic to the field of complex numbers $\mathbb{C}$. The index n thus equals 2 in this case.



Fig. 2. Structure of a Cyclic Division Algebra

B. Cyclic Division Algebras

Our interest is in CDA, i.e., division algebras in which the center $\mathbb{F}$ and a maximum subfield $\mathbb{L}$ are such that $\mathbb{L}/\mathbb{F}$ is a cyclic (Galois) extension. CDAs have a simple characterization that aids in their construction, see [37], Proposition 11 of [20], or Theorem 1 of [22].

Let $\mathbb{F},\ \mathbb{L}$ be number fields, with $\mathbb{L}$ a finite, cyclic Galois extension of $\mathbb{F}$ of degree n. Let σ denote the generator of the Galois group $\mathrm{Gal}(\mathbb{L}/\mathbb{F})$. Let z be an indeterminate satisfying

$$\ell z \ = \ z\sigma(\ell) \quad \forall \ \ \ell \in \mathbb{L} \qquad \text{and} \qquad z^n = \gamma,$$

for some non-norm element $\gamma \in \mathbb{F}^*$, by which we mean some element γ having the property that the smallest positive integer t for which γ^t is the relative norm $N_{\mathbb{L}/\mathbb{F}}(u)$ of some element u in $\mathbb{L}^*$, is n. Then a CDA $D(\mathbb{L}/\mathbb{F}, \sigma, \gamma)$ with index n, center $\mathbb{F}$ and maximal subfield $\mathbb{L}$ is the set of all elements of the form

$$\sum_{i=0}^{n-1} z^i \ell_i, \quad \ell_i \in \mathbb{L}. \tag{6}$$

Moreover it is known that every CDA has this structure. It can be verified that D is a right vector space (i.e., scalars multiply vectors from the right) over the maximal subfield $\mathbb{L}$.

C. Space-Time Codes from Cyclic Division Algebras

A space-time code $\mathcal{X}$ can be associated to D by selecting the set of matrices corresponding to the matrix representation of elements of a finite subset of D. Note that since these matrices are all square matrices, the resultant ST code necessarily has $T = n_t$.

The matrix corresponding to an element $d \in D$ corresponds to the left multiplication by the element d in the division algebra. Let λ_d denote this operation, $\lambda_d : D \to D$, defined by

$$\lambda_d(e) = de, \ \forall \ e \in D.$$

It can be verified that λ_d is a $\mathbb{L}$-linear transformation of D. From (6), a natural choice of basis for the right-vector space D over $\mathbb{L}$ is $\{1, z, z^2, \ldots, z^{n-1}\}$. A typical element in the division algebra D is $d = \ell_0 + z\ell_1 + \cdots + z^{n-1}\ell_{n-1}$, where the $\ell_i \in \mathbb{L}$. By considering the effect of multiplying $d \times 1$, $d \times z$,

$\ldots$, $d \times z^{n-1}$, one can show that the $\mathbb{L}$-linear transformation λ_d under this basis has the matrix representation

$$\begin{bmatrix} \ell_0 & \gamma\sigma(\ell_{n-1}) & \gamma\sigma^2(\ell_{n-2}) & \ldots & \gamma\sigma^{n-1}(\ell_1) \\ \ell_1 & \sigma(\ell_0) & \gamma\sigma^2(\ell_{n-1}) & \ldots & \gamma\sigma^{n-1}(\ell_2) \\ \vdots & \vdots & \vdots & \ddots & \vdots \\ \ell_{n-1} & \sigma(\ell_{n-2}) & \sigma^2(\ell_{n-3}) & \ldots & \sigma^{n-1}(\ell_0) \end{bmatrix}, \quad (7)$$

known as the left regular representation of d.

A set of such matrices, obtained by choosing a finite subset of elements in D constitutes the CDA-based ST code $\mathcal{X}$. The non-commutativity of the CDA endows the codeword matrices with a key determinant property.

Lemma 1: Let A denote the $(n \times n)$ matrix that is the left-regular representation of the element

$$\psi \;=\; \sum_{i=0}^{n-1} \ell_i z^i, \quad \ell_i \in \mathbb{L}.$$

Then $\det(A) \in \mathbb{F}$.

Proof: While this result is known (see [38] for example), a short proof is included in Appendix III for the sake of completeness. ■

D. Endowing the NVD Property

In this section, we follow [8], [12], [22] and show how a CDA-based ST code with NVD can be constructed for the case when the underlying constellation is the QAM constellation. The construction can be extended (see [23]) to other constellations such as the HEX constellation. Appendix I provides a primer on the relevant number theory. Appendix II provides constructions for the HEX constellation.

The $\mathcal{A}_{\text{QAM}}$ constellation has the property that

$$u \in \mathcal{A}_{\text{QAM}} \;\Rightarrow |\, u \,|^2 \leq 2M^2.$$

Since

$$\mathcal{A}_{\text{QAM}} \;\subseteq\; \mathbb{Q}(\imath)$$

it is natural to consider CDA with center $\mathbb{F} \;=\; \mathbb{Q}(\imath)$.

Let $\mathbb{F} \;=\; \mathbb{Q}(\imath)$, $\mathbb{L}$ be a n-degree cyclic Galois extension $\mathbb{L}/\mathbb{F}$ of $\mathbb{F}$ and let σ be the generator of the Galois group $\text{Gal}(\mathbb{L}/\mathbb{F})$. Let $\mathcal{O}_{\mathbb{F}}, \mathcal{O}_{\mathbb{L}}$ denote the ring of algebraic integers in $\mathbb{F}, \mathbb{L}$ respectively. It is known that $\mathcal{O}_{\mathbb{F}} = \mathbb{Z}[\imath]$. Let $\gamma \;\in\; \mathcal{O}_{\mathbb{F}}$, $\gamma \neq 0$, be a non-norm element and $D(\mathbb{L}/\mathbb{F}, \sigma, \gamma)$ denote the associated CDA.

Let $\{\beta_1, \ldots, \beta_n\}$ form an integral basis for $\mathcal{O}_{\mathbb{L}}/\mathcal{O}_{\mathbb{F}}$ and define the set

$$\mathcal{A}_{\text{QAM}}(\beta_1, \beta_2, \ldots, \beta_n) \;=\; \left\{ \sum_i a_i \beta_i \mid a_i \in \mathcal{A}_{\text{QAM}} \right\}.$$

Thus $\mathcal{A}_{\text{QAM}}(\beta_1, \beta_2, \ldots, \beta_n)$ is the set of all linear combinations of the basis elements β_i with coefficients lying in $\mathcal{A}_{\text{QAM}}$.

Consider the space-time code $\mathcal{X}$ comprising of matrices corresponding to the left-regular representation as in (7) of all elements d in CDA D which are of the form

$$d = \sum_{i=0}^{n-1} z^i \ell_i \;, \quad \ell_i \in \mathcal{A}_{\text{QAM}}(\beta_1, \beta_2, \ldots, \beta_n).$$

From Lemma 1, it follows that the determinant of every such left-regular representation lies in $\mathbb{F} \;=\; \mathbb{Q}(\imath)$. But since all entries of the regular representation lie in the ring $\mathcal{O}_{\mathbb{L}}$, it follows that the determinant must moreover, lie in

$$\mathcal{O}_{\mathbb{L}} \cap \mathbb{F} \;=\; \mathcal{O}_{\mathbb{F}} \;=\; \mathbb{Z}[\imath].$$

The NVD property of the ST code constructed now follows since the difference of any two elements in the CDA is also an element of the CDA and since the magnitude of any nonzero element in $\mathbb{Z}[\imath]$ is ≥ 1.

E. Proof of D-MG Optimality of CDA-Based ST Codes having the NVD Property

Theorem 2 (Proof of D-MG Optimality): Let $T = n_t = n$. Let the CDA-based ST code $\mathcal{X}$ be constructed as above and let $\mathcal{Z}$ denote the normalized code

$$\mathcal{Z} \;=\; \{\theta X \;\mid\; X \in \mathcal{X}\}$$

where θ is chosen to ensure that

$$||\theta X||_F^2 \;\leq\; T \text{ SNR}, \quad \text{all } X \in \mathcal{X}. \quad (8)$$

Then the ST code $\mathcal{Z}$ is optimal with respect to the D-MG tradeoff for any number n_r of receive antennas.

Proof: We will use the NVD property in conjunction with the sphere bound to prove optimality of the code. The requirement of transmitting information at rate $r\log(\text{SNR})$ forces $M^2 \;=\; \text{SNR}^{\frac{r}{n}}$. The energy requirement (8) then forces $\theta^2 \;\doteq\; \text{SNR}^{1-\frac{r}{n}}$. Let $m = \min\{n_t, n_r\}$ and $n_\Delta = |n_t - n_r|$. Let $\theta X_0,\; X_0 \in \mathcal{X}$ be the transmitted code matrix and X_1 be any other code matrix distinct from X_0. Set $\Delta X = X_0 - X_1$. Let

$$\begin{aligned} \lambda_1 \geq \lambda_2 \geq \cdots \geq \lambda_{n_t} \geq 0 \\ 0 \leq l_1 \leq l_2 \leq \cdots \leq l_{n_t} \end{aligned} \quad (9)$$

denote the eigenvalues of $H^\dagger H$ and $\Delta X \Delta X^\dagger$ respectively. Note that only the first m eigenvalues $\{\lambda_i\}_{i=1}^m$ are nonzero. We have the lower bound

$$\begin{aligned} d_E^2 &= \theta^2 \text{Tr}(H\Delta X\Delta X^\dagger H^\dagger) && (10) \\ &\geq \theta^2 \sum_{i=1}^{n} l_i \lambda_i && (11) \\ &\geq \theta^2 \sum_{i=1}^{k} \lambda_i l_i \quad 1 \leq k \leq m && (12) \\ &\geq \theta^2 k \left[\prod_{i=1}^{k} \lambda_i\right]^{\frac{1}{k}} \left[\prod_{i=1}^{k} l_i\right]^{\frac{1}{k}} \quad \text{(by AM-GM)} && (13) \\ &\geq k\theta^2 \text{SNR}^{-\frac{1}{k}\sum_{i=1}^{k}\alpha_i} \left[\frac{\text{SNR}^0}{\text{SNR}^{(n-k)\frac{r}{n}}}\right]^{\frac{1}{k}} && (14) \\ &\doteq \text{SNR}^{-\frac{1}{k}\left\{\sum_{i=1}^{k}\alpha_i + r - k\right\}}, \quad 1 \leq k \leq m, && (15) \end{aligned}$$

where we have set $\lambda_i = \text{SNR}^{-\alpha_i}$.

Inequality (11) is due to Köse and Wesel [45] and a proof is provided in Appendix III for the sake of completeness [3]. In

---

[3] The original submission of this paper contained an independent proof of this result as we were unaware at the time of the results in [45].

(18), we used the NVD property of the CDA-based ST code as well as the fact that every eigenvalue l_i is upper bound by $\text{Tr}(\Delta X \Delta X^\dagger) \dot{\le} M^2 \doteq \text{SNR}^{\frac{r}{n}}$.

By the sphere bound, given the channel matrix H, the probability of codeword error $\Pr(\mathcal{E}|H)$ is upper bounded by the probability that the additive noise W causes the received matrix to lie outside a ball of radius $d_{E,\min}/2$ where $d_{E,\min}$ is the minimum in the set $\{||[\theta H(X_0 - X_1)]||_F \mid X_1 \in \mathcal{X}\}$. Our bound for d_E above is independent of the particular pair of codewords X_0, X_1, hence serves as a lower bound to $d_{E,\min}$ and can be used in place of $d_{E,\min}$ in the sphere bound.

The random variable $||W||_F^2$ is a chi-squared random variable in $2n_rT$ dimensions satisfying

$$\Pr\left(||W||_F^2 > \frac{d_{E,\min}^2}{4}\right) = \exp\left(-\frac{d_{E,\min}^2}{4}\right) \sum_{k=0}^{n_rT-1} \frac{\left(\frac{d_{E,\min}^2}{4}\right)^k}{k!} \tag{16}$$

Using the density function of the $\{\alpha_i\}$ derived in [1], and averaging over all channel realizations, we obtain

$$\begin{aligned} \Pr(\mathcal{E}) &= \mathbb{E}_H(\Pr(\mathcal{E}|H)) \\ &\le \int_{\underline{\alpha}} \mathcal{K}\ [\log(\text{SNR})]^m \exp(-(\sum_{i=1}^m \text{SNR}^{-\alpha_i}) \\ &\quad \text{SNR}^{-\sum_{i=1}^m \alpha_i [n_\Delta + 2i - 1]} \\ &\quad\quad \exp(-\text{SNR}^{-\frac{1}{k}(\sum_{i=1}^k \alpha_i + r - k)}) \\ &\quad \left[\sum_{j=0}^{n_r-1} \frac{\text{SNR}^{-\frac{j}{k}(\sum_{i=1}^k \alpha_i + r - k)}}{j!}\right] d\underline{\alpha} \\ &\doteq \text{SNR}^{-e(r)} \end{aligned}$$

where $\mathcal{K}$ is a constant and where

$$e(r) = \inf_{\substack{\alpha_k \ge 0 \\ \sum_{i=1}^k \alpha_i \ge k - r \\ 1 \le k \le m}} \sum_{i=1}^m \alpha_i (n_\Delta + 2(m+1-r) - 1).$$

We find after some work that $e(r)$ is equal to the piecewise linear function given by

$$e(r) = (n_t - r)(n_r - r)$$

for integral values of r.

■

A closer examination of the proof of Theorem 2 will reveal that the following more general result is true.

Theorem 3 (Sufficient Condition for Optimality): Consider a $n_t \times T$ space-time code $\mathcal{X}$ with $T \ge n_t$ indexed by a rate parameter r such that when the space-time code has size SNR^{rT} and when each normalized code matrix $Z \in \mathcal{Z} = \{\theta X \mid X \in \mathcal{X}\}$ satisfies the energy requirement $||Z||_F^2 \le T$ SNR, we have

$$\min_{\substack{\Delta Z = Z_i - Z_j \neq 0 \\ Z_i, Z_j \in \mathcal{Z}}} \det(\Delta Z \Delta Z^\dagger) \dot{\ge} \text{SNR}^{n_t - r}.$$

Then over the quasi-static i.i.d. Rayleigh-fading channel, the normalized ST code $\mathcal{Z}$ is optimal with respect to the D-MG tradeoff for any number n_r of receive antennas.

Proof: Let $\mu_i = \theta^2 l_i$, $\mu_1 \le \mu_2 \le \cdots \le \mu_n$ denote the eigenvalues of $\Delta Z \Delta Z^\dagger$. From the energy constraint it follows that $\mu_i \dot{\le}$ SNR. Proceeding now as in the proof of Theorem 2, we obtain

$$\begin{aligned} d_E^2 &\ge k \left[\prod_{i=1}^k \lambda_i\right]^{\frac{1}{k}} \left[\prod_{i=1}^k \mu_i\right]^{\frac{1}{k}}, \quad 1 \le k \le m & (17) \\ &\ge k\ \text{SNR}^{-\frac{1}{k}\sum_{i=1}^k \alpha_i} \left[\frac{\text{SNR}^{n-r}}{\text{SNR}^{n-k}}\right]^{\frac{1}{k}} & (18) \\ &\doteq \text{SNR}^{-\frac{1}{k}\{\sum_{i=1}^k \alpha_i + r - k\}}, \quad 1 \le k \le m, & (19) \end{aligned}$$

where $m = \min\{n_r, n_t\}$ as before. The rest of the proof now proceeds as before. ■

We note that the theorem above can also be derived from the results in [27].

III. CONSTRUCTION OF D-MG OPTIMAL SQUARE ST CODES DERIVED FROM CDA

By a square ST code, we will mean a ST code in which $T = n_t$ and we will use n to denote their common value. In this section, we will present a construction of D-MG optimal square $(n \times n)$ ST codes derived from CDA. From the discussion in Section II, it follows that the problem of constructing D-MG optimal ST codes from CDA reduces to one of identifying cyclic Galois extensions $\mathbb{L}$ of arbitrary degree n over $\mathbb{F} = \mathbb{Q}(\imath)$ containing a suitable non-norm element γ. Prior to the present paper, these had only been achieved for certain restricted values of n. In [8], [11], [12], constructions were provided for values of $n = 2, 3, 4, 6$, while in a more recent advancement [24], constructions are provided for $n = 2^k, 3.2^k, q^k(q-1)/2$, where k is an arbitrary integer and q is a prime of the form $4s+3,\ s \in \mathbb{Z}$.

Two general constructions will now be presented, both valid for all values of the integer n. We begin with a lemma.

Lemma 4: [24] Let $\mathbb{K}$ be a cyclic extension of a number field $\mathbb{F}$. Let $\mathcal{O}_\mathbb{F}$ denote the ring of integers of $\mathbb{F}$. Let $\mathfrak{p}$ be a prime ideal of $\mathcal{O}_\mathbb{F}$ that remains inert in the extension $\mathbb{K}/\mathbb{F}$ and let $\gamma \in \mathfrak{p} \setminus \mathfrak{p}^2$. Then γ is a non-norm element.

It follows from this lemma, that for constructing D-MG optimal square $(n \times n)$ ST codes from CDA, it is sufficient to construct cyclic extensions of $\mathbb{Q}(\imath)$ of degree n such that $\mathcal{O}_\mathbb{F}$ contains a prime ideal $\mathfrak{p}$ that remains inert in the extension.

A. Construction A

Let the integer n be factored as follows:

$$n = 2^{e_0} \prod_{i=1}^r p_i^{e_i} = 2^{e_0} n_1 \tag{20}$$

where the $\{p_i\}$ are distinct odd primes. Given an integer $m \ge 3$, we define $\omega_m = \exp(\imath \frac{2\pi}{m})$.

Construction A begins by identifying two cyclotomic extensions, one of which contains a cyclic extension $\mathbb{M}$ of $\mathbb{Q}(\imath)$ of degree n_1 and the second of which contains a cyclic extension $\mathbb{Q}(\omega_{2^{e_0+2}})$ of $\mathbb{Q}(\imath)$ of degree 2^{e_0} (see Fig. 3). Both extensions moreover, contain prime ideals that remain inert. Then we show how the two extensions can be made to yield a cyclic extension $\mathbb{L}$ of $\mathbb{Q}(\imath)$ of degree n also containing an inert prime ideal.

Proposition 5: (Dirichlet's theorem)
Let a, m be integers such that $1 \leq a < m$ and $\gcd(a, m) = 1$. Then the arithmetic progression

$$\{a, a+m, a+2m, \ldots, a+km, \ldots\}$$

contains infinitely many prime numbers.

Applying Dirichlet's theorem, Proposition 5, to the arithmetic progression

$$\{1, 1+n_1, 1+2n_1, \ldots, 1+kn_1, \ldots\},$$

we see that we are always guaranteed to find a prime p such that $n_1|(p-1)$. Given this, we define the prime p and the exponent $e \geq 1$ such that p^e is the smallest prime power such that $n_1|(\phi(p^e))$ (where ϕ is Euler's totient function).

Lemma 6: The cyclotomic extension $\mathbb{Q}(\omega_{p^e})$ contains a subfield $\mathbb{K}$ that is a cyclic extension of $\mathbb{Q}$ of degree n_1.

Proof: Let G denote the Galois group Gal$(\mathbb{Q}(\omega_{p^e})/\mathbb{Q})$. Then by Corollary 22, G is cyclic of size $\phi(p^e) = p^{e-1}(p-1)$ and isomorphic to $\mathbb{Z}_{p^e}^*$. Since $n_1 \mid \phi(p^e)$, it follows that G contains a unique cyclic subgroup H of index n_1, i.e., of size $\phi(p^e)/n_1$.

From the fundamental theorem of Galois theory, Proposition 16, there is a unique subfield $\mathbb{K}$ of $\mathbb{Q}(\omega_{p^e})$ which is fixed by the subgroup H such that $\mathbb{Q} \subseteq \mathbb{K} \subseteq \mathbb{Q}(\omega_{p^e})$. Moreover, $[\mathbb{K} : \mathbb{Q}] = n_1$ and Gal$(\mathbb{K}/\mathbb{Q}) \approx G/H$. Thus to show that $\mathbb{K}/\mathbb{Q}$ is cyclic, it is sufficient to show that G/H is cyclic and this follows from Lemma 15. ■



Fig. 3. The number fields appear in Construction A. n is the designed cyclic extension.

Lemma 7: There exists a rational prime q_1 such that the ideal (q_1) is inert in $\mathbb{Q}(\omega_{p^e})/\mathbb{Q}$.

Proof: Let ρ be a generator of the cyclic group $\mathbb{Z}_{p^e}^*$. Hence ρ has order $\phi(p^e)$. By Dirichlet's theorem, Proposition 5, applied to the arithmetic progression

$$\{\rho, \rho+p^e, \rho+2p^e, \ldots, \rho+kp^e, \ldots\}$$

there exists a prime $q_1 \equiv \rho \pmod{p^e}$. From Lemma 24 it follows that (q_1) is inert in $\mathbb{Q}(\omega_{p^e})/\mathbb{Q}$. ■

Our next aim is to construct a cyclic extension of $\mathbb{Q}(\imath)$ of degree 2^{e_0} that contains an inert prime ideal. If $e_0 = 0$, then $\mathbb{Q}(\imath)$ itself is the desired extension and we are done.

For $e_0 \geq 1$, the group $\mathbb{Z}_{2^{e_0+2}}^*$ is not cyclic by Lemma 19 and so one cannot hope to find a rational prime q which remains inert in the extension $\mathbb{Q}(\omega_{2^{e_0+2}})/\mathbb{Q}$. However, it turns out that one can always find a prime q such that the ideal (q) splits into the product $(q) = \beta_1\beta_2$ of prime ideals $\beta_i, i = 1, 2$ in the extension $\mathbb{Q}(\imath)/\mathbb{Q}$ with each of the prime ideals β_i remaining inert in the extension $\mathbb{Q}(\omega_{2^{e_0+2}})/\mathbb{Q}(\imath)$ and this turns out to be sufficient for our purposes (see Fig. 4). We begin by showing that the extension $\mathbb{Q}(\omega_{2^{e_0+2}})/\mathbb{Q}(\imath)$ is cyclic.

Lemma 8: $\mathbb{Q}(\omega_{2^{e_0+2}})/\mathbb{Q}(\imath)$ is a cyclic Galois extension of degree 2^{e_0}.

Proof: From Lemma 20, the maximal order of an element in $\mathbb{Z}_{2^{e_0+2}}^*$ equals 2^{e_0}. The element 5 in $\mathbb{Z}_{2^{e_0+2}}^*$ has this maximal possible order. This follows since every element must have order dividing $\phi(2^{e_0+2}) = 2^{e_0+1}$ and $5^{2^{e_0-1}} \equiv (1 + 2^2)^{2^{e_0-1}} \equiv 1 + 2^{e_0-1}.2^2 \not\equiv 1 \pmod{2^{e_0+2}}$. Next, consider the automorphisms $\sigma_k, 0 \leq k \leq 2^{e_0} - 1$, of $\mathbb{Q}(\omega_{2^{e_0+2}})/\mathbb{Q}$ given by

$$\sigma_k(\omega_{2^{e_0+2}}) \;=\; \omega_{2^{e_0+2}}^{5^k}, \quad 0 \leq k \leq 2^{e_0} - 1.$$

These automorphisms form a cyclic group of order 2^{e_0} and the fixed field of this group is $\mathbb{Q}(\imath)$ since $\imath^{5^k} = \imath$, all k. It follows that $\mathbb{Q}(\omega_{2^{e_0+2}})/\mathbb{Q}(\imath)$ is cyclic of degree 2^{e_0}. ■

Lemma 9: There exists a prime ideal β such that β is inert in $\mathbb{Q}(\omega_{2^{e_0+2}})/\mathbb{Q}(\imath)$.

Proof: Let p be a prime such that $p \equiv 1 \pmod 4$. Then it follows from Lemma 23 and Lemma 24 that both the ramification index e as well as the relative degree f of the prime ideal $p\mathbb{Z}[\imath]$ in the extension $\mathbb{Q}(\imath)/\mathbb{Q}$ equal 1. It follows that the index g of the decomposition group of $p\mathbb{Z}$ equals 2, i.e., that the ideal $p\mathbb{Z}[\imath]$ splits into the product

$$p\mathbb{Z}[\imath] \;=\; \beta_1\beta_2$$

of distinct prime ideals β_1, β_2.

Next let us impose the further condition that $p \equiv 5 \pmod{2^{e_0+2}}$ which is consistent with $p \equiv 1 \pmod 4$. Consider the decomposition of $p\mathbb{Z}$ in the larger extension $\mathbb{Q}(\omega_{2^{e_0+2}})/\mathbb{Q}$. From the proof of Lemma 8, it follows that the order of $p \pmod{2^{e_0+2}}$ equals 2^{e_0}. Thus the relative degree f of the prime ideal $p\mathbb{Z}[\omega_{2^{e_0+2}}]$ equals 2^{e_0}. Since $\phi(2^{e_0+2}) = 2^{e_0+1}$ and the ideal $p\mathbb{Z}[\omega_{2^{e_0+2}}]$ is unramified, it follows from equation (33) that the index g of the corresponding decomposition group equals 2 so that the ideal generated by p in the ring of integers $\mathbb{Z}[\omega_{2^{e_0+2}}]$ of $\mathbb{Q}(\omega_{2^{e_0+2}})$, factors into the product of two prime ideals.

It follows now from (35) that both prime ideals β_i remain inert in the extension $\mathbb{Q}(\omega_{2^{e_0+2}})/\mathbb{Q}(\imath)$. ■


$\beta_1\mathcal{O}_{\mathbb{L}}$
$\beta_1\mathbb{Z}[\omega_{2^{e_0+2}}]$
$f{=}n$
$g{=}1$
$\beta_1\mathcal{O}_{\mathbb{M}}$
$q\mathbb{Z}[\omega_{p^e}]$
$g{=}1$
$f{=}n_1$
$f{=}2^{e_0}$
$g{=}1$
$\beta_1\mathbb{Z}[\imath]$
$f{=}n_1$
$g{=}2$
$q\mathcal{O}_{\mathbb{K}}$
$g{=}2$
$f{=}n_1$
$f{=}1$
$g{=}1$
$q\mathbb{Z}$

Fig. 4. Prime ideal decomposition in the number fields of Construction A. Note that although $q\mathbb{Z}$ decomposes into the product of two prime ideals in the extensions $\mathbb{Q}(\imath)/\mathbb{Q}$ and $\mathbb{M}/\mathbb{Q}$, we have shown only one of the two prime ideals in the figure for the sake of clarity, namely the one generated by β_1.

Theorem 10 (Construction A): Let

$$n \;=\; 2^{e_0}n_1 \tag{21}$$

where n_1 is odd. Let p^e be the smallest prime power such that $n_1|\phi(p^e)$. Let G be the Galois group of $\mathbb{Q}(\omega_{p^e})/\mathbb{Q}$. Let H be a subgroup of G of size $\phi(p^e)/n_1$. Let $\mathbb{K}$ be the fixed field of H. Let $\mathbb{M}$ be the compositum of $\mathbb{K}$ and $\mathbb{Q}(\imath)$ and $\mathbb{L}$ the compositum of $\mathbb{M}$ and $\mathbb{Q}(\omega_{2^{e_0+2}})$. Then $\mathbb{L}$ is the desired cyclic extension of $\mathbb{Q}(\imath)$ of degree n (Fig. 3).

Let $\rho \in \mathbb{Z}^*_{p^e}$ be a generator of the cyclic group $\mathbb{Z}^*_{p^e}$. Let q be a rational prime such that

$$q \;=\; \begin{cases} \rho & \pmod{p^e} \\ 5 & \pmod{2^{e_0+2}} \end{cases}. \tag{22}$$

Let β be a prime ideal of $\mathbb{Z}[\imath]$ lying above $q\mathbb{Z}$ in $\mathbb{Q}(\imath)/\mathbb{Q}$. Then β is the desired prime that remains inert in the extension $\mathbb{L}/\mathbb{Q}(\imath)$.

Proof: From Lemma 6 we know that $\mathbb{K}/\mathbb{Q}$ is a cyclic extension of odd degree n_1. It is clear that $\mathbb{Q}(\imath)/\mathbb{Q}$ is cyclic of degree 2. It follows from Lemma 17 that the compositum $\mathbb{M} = \mathbb{K}{\cdot}\mathbb{Q}(\imath)$ is a cyclic extension of $\mathbb{Q}$ of degree $2n_1$. Since $\mathbb{M}/\mathbb{Q}$ is cyclic, it follows that the extension $\mathbb{M}/\mathbb{Q}(\imath)$ is cyclic of degree n_1 as well. From Lemma 8 we know that $\mathbb{Q}(\omega_{2^{e_0+2}})/\mathbb{Q}(\imath)$ is cyclic of degree 2^{e_0}. It follows now from a second application of Lemma 17 that $\mathbb{L}/\mathbb{Q}(\imath)$ is cyclic of degree n as desired.

To prove that the ideal β is inert in the extension $\mathbb{L}/\mathbb{Q}(\imath)$, we note first of all that by the Chinese Remainder theorem and Dirichlet's theorem, Proposition 5, a prime q satisfying (22) is guaranteed to exist. Next we observe that

1) the index of the decomposition group of $q\mathbb{Z}$ in $\mathbb{Q}(\imath)/\mathbb{Q}$ equals 2. Hence from (36), the index of the decomposition group of $q\mathbb{Z}$ in $\mathbb{M}/\mathbb{Q}$ must be a multiple of 2,
2) the relative degree of $q\mathbb{Z}$ in the extension $\mathbb{K}/\mathbb{Q}$ equals n_1, hence the relative degree of $q\mathbb{Z}$ in the extension $\mathbb{M}/\mathbb{Q}$ must be a multiple of n_1.

On the other hand, we have that the degree of the extension $\mathbb{M}/\mathbb{Q}$ equals $2n_1$ and hence it follows from equation (33) of Appendix I that the index of the decomposition group of $q\mathbb{Z}$ in $\mathbb{M}/\mathbb{Q}$ equals 2 and the relative degree of $q\mathbb{Z}$ in the extension $\mathbb{M}/\mathbb{Q}$ equals n_1.

Since the index of the decomposition group of $q\mathbb{Z}$ in $\mathbb{Q}(\imath)/\mathbb{Q}$ equals 2, $q\mathbb{Z}$ factors into the product of two ideals $\beta_1\beta_2$ in this extension. Without loss of generality, we set $\beta = \beta_1$. An application of equation (35) of Appendix I, then tells us that the relative degree of the ideal β in the extension $\mathbb{M}/\mathbb{Q}(\imath)$ equals n_1, i.e., that the ideal is inert in this extension. Since the ideal β is inert even in the extension $\mathbb{Q}(\omega_{2^{e_0+2}})/\mathbb{Q}(\imath)$, it follows once again from (35), that the ideal $\beta\mathbb{Z}[\imath]$ remains inert in the extension $\mathbb{L}/\mathbb{Q}(\imath)$ where $\mathbb{L}$ is the compositum of the fields $\mathbb{Q}(\omega_{2^{e_0+2}})$ and $\mathbb{M}$ (see Fig. 4). ■

B. Construction B

Theorem 11 (Construction B): Let

$$n \;=\; 2^{e_0}\prod_{i=1}^{r} p_i^{e_i} \;=\; 2^{e_0}n_1 \tag{23}$$

where p_i are distinct odd primes. Let $\rho_i, 1 \le i \le r$ be elements of $\mathbb{Z}^*_{p_i^{e_i+1}}$ having maximum possible multiplicative order $p_i^{e_i}$. Let ρ be the element of $\mathbb{Z}^*_n$ satisfying

$$\rho \;\equiv\; \begin{cases} \rho_i \pmod{p_i^{e_i+1}}, & 1 \le i \le r \\ 5 \pmod{2^{e_0+2}}. \end{cases} \tag{24}$$

Let H_i be the unique cyclic subgroup of Gal $\left(\mathbb{Q}(\omega_{p_i^{e_i+1}})/\mathbb{Q}\right)$ of index $p_i^{e_i}$, $1 \le i \le r$. Let $\mathbb{F}_i, 1 \le i \le r$ be the fixed field of H_i. Let $\mathbb{K}$ be the compositum of the $(r+1)$ fields $\mathbb{Q}(\imath)$, $\{\mathbb{F}_i\}_{i=1}^r$ and let $\mathbb{L}$ be the compositum of $\mathbb{K}$ and $\mathbb{Q}(\omega_{2^{e_0+2}})$ (Fig. 5, 6). Then

1) there exists a prime $q \;\equiv\; \rho \pmod{n}$
2) $\mathbb{L}$ is a cyclic extension of $\mathbb{Q}(\imath)$ of degree n
3) the ideal generated by $q\mathbb{Z}$ factors into the product of two prime distinct ideals $\beta_i, i = 1, 2$ in the ring of algebraic integers of $\mathbb{Z}[\imath]$, i.e.,

$$q\mathbb{Z} \;=\; \beta_1\beta_2$$

4) each of the two ideals β_i remains inert in the field extension $\mathbb{L}/\mathbb{Q}(\imath)$

Proof: The same argument used in the proof of Lemma 6 to show that the extension $\mathbb{K}/\mathbb{Q}$ is cyclic, shows that each of the fields $\mathbb{F}_i$ are cyclic extensions of $\mathbb{Q}$ of degree $p_i^{e_i}, 1 \le i \le r$ and that $q\mathbb{Z}$ remains inert in the extension $\mathbb{F}_i/\mathbb{Q}$. Since the extensions $\mathbb{F}_i/\mathbb{Q}$ have degrees that are relatively prime, it follows that $\mathbb{K}/\mathbb{Q}$ is a cyclic extension of degree $n_1 = \prod_{i=1}^r p_i^{e_i}$. Moreover, since $q\mathbb{Z}$ remains inert in each of the extensions $\mathbb{F}_i/\mathbb{Q}$, it follows from (35) and (33) that $q\mathbb{Z}$ remains inert in the extension $\mathbb{K}/\mathbb{Q}$.

We are now in a similar situation as in the case of Construction A. The only difference is the manner in which the field $\mathbb{K}$ was constructed. Thus by following the remainder of the proof of Theorem 10, the proof of the present proposition follows. ■



Fig. 5. Constructing the cyclic extension $\mathbb{K}/\mathbb{Q}$ of Construction B.



Fig. 6. Construction B with $\mathbb{K}$ constructed as in Fig. 5.

TABLE I

NON-NORM ELEMENTS FOR USE IN CONSTRUCTION A

No. n_t of Antennas	p^e	q	Non-norm 'γ'
2	8	5	$(2+\imath)$
3	7	5	$(2+\imath)$
4	8	5	$(2+\imath)$
5	11	13	$(3+2\imath)$
6	7	5	$(2+\imath)$
7	29	37	$(6+\imath)$
8	8	5	$(2+\imath)$
9	19	29	$(5+2\imath)$
10	11	13	$(3+2\imath)$
11	23	5	$(2+\imath)$
12	7	5	$(2+\imath)$
13	53	5	$(2+\imath)$
14	29	36	$(6+\imath)$
15	31	53	$(7+2\imath)$
16	8	5	$(2+\imath)$
17	103	5	$(2+\imath)$
18	19	13	$(3+2\imath)$
19	191	29	$(5+2\imath)$
20	11	13	$(3+2\imath)$

TABLE II

NON-NORM ELEMENTS FOR USE IN CONSTRUCTION B

No. n_t of Antennas	prime 'q'	Non-norm 'γ'
2	5	$(2+\imath)$
3	5	$(2+\imath)$
4	5	$(2+\imath)$
5	13	$(3+2\imath)$
6	5	$(2+\imath)$
7	5	$(2+\imath)$
8	5	$(2+\imath)$
9	5	$(2+\imath)$
10	13	$(3+2\imath)$
11	13	$(3+2\imath)$
12	5	$(2+\imath)$
13	37	$(6+\imath)$
14	5	$(2+\imath)$
15	113	$(7+8\imath)$
16	5	$(2+\imath)$
17	5	$(2+\imath)$
18	5	$(2+\imath)$
19	13	$(3+2\imath)$
20	37	$(6+\imath)$

Having explicitly described the method for constructing γ for any number of antennas, we proceed in Tables I, II, to present example values of γ for n_t in the range $2 \leq n_t \leq 20$ corresponding to Constructions A and B respectively.

IV. CONSTRUCTIONS FOR THE RECTANGULAR CASE

For the purposes of simplifying the exposition in this section, we will use the term *clearly optimal* $(n_t \times T)$ ST code to refer to a normalized $n_t \times T$ space-time code $\mathcal{Z}$ with $T \geq n_t$, indexed by a rate parameter r such that when

(i) the space-time code has size SNR^{rT} and when

(ii) each normalized code matrix $Z \in \mathcal{Z}$ satisfies

$$||Z||_F^2 \;\leq\; T\ \text{SNR},$$

(iii) we have

$$\min_{\substack{\Delta Z = Z_i - Z_j \neq 0 \\ Z_i, Z_j \in \mathcal{Z}}} \det(\Delta Z \Delta Z^\dagger) \;\dot{\geq}\; \text{SNR}^{n_t - r}.$$

It follows from Theorem 3, that a clearly optimal ST code is D-MG optimal for any number n_r of receive antennas.

Two general techniques will now be presented that enable the construction of clearly optimal rectangular $(n_t \times T)$ ST codes for every pair (n_t, T) with $T > n_t$ from clearly optimal square ST codes of the appropriate dimension.

Both techniques will be shown to yield ST codes that achieve the upper bound on the optimal D-MG tradeoff for all $T \geq n_t$ (and all n_r for a given T) given by

$$d(r) \;=\; (n_t - r)(n_r - r) \tag{25}$$

for integer r and by straight-line interpolation for non-integer values. This will not only establish the D-MG optimality of these construction techniques, but show in addition that for all $T \geq n_t$, the D-MG tradeoff is given precisely by (25). Previously, from [1], this was known to hold only for all $T \geq n_t + n_r - 1$.

The first technique, which we term the row-deletion construction, shows that a clearly optimal square ST code remains clearly optimal even if an arbitrary number of rows from the matrix is deleted.

The second construction, called the Cartesian-product construction, shows that codewords from a collection of clearly optimal $(n_t \times T_i)$ ST codes can be horizontally stacked to yield a clearly optimal ST code of larger length $T = \sum_i T_i$.

A. The Row-Deletion Construction

Theorem 12 (Row-Deletion Construction): Let $T > n_t$. Let $\mathcal{Z}_S$ be a clearly optimal $(T \times T)$ square ST code. Next, let $\mathcal{Z}_R$ be the $(n_t \times T)$ rectangular ST code obtained by deleting a particular set of $(T - n_t)$ rows from every code matrix $Z \in \mathcal{Z}_S$. Then the $(n_t \times T)$ ST code $\mathcal{Z}_R$ is also clearly optimal.

Proof: We note first that the ST code $\mathcal{Z}_S$ has the property that the message symbols can be uniquely recovered given either a single row or a single column of the code matrix. This follows since no two code matrices in $\mathcal{Z}_S$ can agree in any single row or column, for, otherwise, their difference would have determinant equal to zero.

Next we observe that if Z_R is a $(n_t \times T)$ matrix obtained from a $(T \times T)$ ST code matrix $Z_S \in \mathcal{Z}_S$, by deleting some $(T - n_t)$ rows, then $\Delta Z_R \Delta Z_R^\dagger$ is a $(n_t \times n_t)$ principal submatrix of $\Delta Z_S \Delta Z_S^\dagger$. Let

$$\mu_1 \leq \mu_2 \leq \cdots \leq \mu_{n_t} \tag{26}$$

$$\nu_1 \leq \nu_2 \leq \cdots \leq \nu_{n_t} \leq \cdots \leq \nu_T \tag{27}$$

be the ordered eigenvalues of $\Delta Z_R \Delta Z_R^\dagger$ and $\Delta Z_S \Delta Z_S^\dagger$ respectively. By the inclusion principle of Hermitian matrices, (see Theorem 4.3.15 of [39]) the smallest eigenvalues of $\Delta Z_R \Delta Z_R^\dagger$ are larger than the corresponding smallest eigenvalues of $\Delta Z_S \Delta Z_S^\dagger$, i.e.,

$$\mu_k \;\geq\; \nu_k, \quad 1 \leq k \leq n_t.$$

Since $||\Delta Z_S||_F^2 \stackrel{.}{\leq} \text{SNR}$, it follows that every eigenvalue ν_k of $\Delta Z_S \Delta Z_S^\dagger$ is bounded above by SNR. If the ST code $\mathcal{Z}_S$ is designed to operate at rate $r \log(\text{SNR})$ bits per channel use, then we have

$$\begin{aligned} \det(\Delta Z_R \Delta Z_R^\dagger) &\stackrel{.}{\geq} \frac{\text{SNR}^{T-r}}{\text{SNR}^{T-n_t}} \\ &= \text{SNR}^{n_t - r} \end{aligned}$$

and it follows that the row-deleted code is also clearly optimal. ■

Example *2:* (Row-Deleted ST Code Derived from CDA) The CDA-based square ST codes presented in Section III constitute an example of clearly optimal ST code. From (7), each codeword Z in the row-deleted $(n_t \times T)$ normalized ST code $\mathcal{Z}$ takes on the form

$$Z = \theta \begin{bmatrix} \ell_0 & \gamma\sigma(\ell_{T-1}) & \cdots & \gamma\sigma^{T-1}(\ell_1) \\ \ell_1 & \sigma(\ell_0) & \cdots & \gamma\sigma^{T-1}(\ell_2) \\ \vdots & \vdots & \ddots & \vdots \\ \ell_{n_t-1} & \sigma(\ell_{n_t-2}) & \cdots & \gamma\sigma^{T-1}(\ell_{n_t}) \end{bmatrix}. \tag{28}$$

B. The Cartesian-Product Construction

Theorem 13 (Cartesian-Product Construction): Let n_t, T be given, $T > n_t$. Let T be partitioned into the integers $T_k \geq n_t, \ 1 \leq k \leq K$, satisfying $\sum_{k=1}^K T_k = T$. Let $\{\mathcal{Z}^{(i)}\}_{i=1}^K$ be a collection of K clearly optimal ST codes of size $(n_t \times T_k)$. Then the Cartesian product

$$\mathcal{Z} \;=\; \bigotimes_{k=1}^{K} \mathcal{Z}^{(k)}$$

comprised of $(n_t \times T)$ code matrices of the form

$$Z \;=\; [Z^{(1)} \; Z^{(2)} \ldots Z^{(K)}], \quad Z_i \in \mathcal{Z}^{(i)}$$

is also clearly optimal.

Proof: It is clear that if each individual code matrix $Z^{(k)} \in \mathcal{Z}^{(k)}$, satisfies the energy and rate requirements, the same is true of the product code. It remains to verify that the determinant condition is met. Consider the difference

$$\begin{aligned} \Delta Z &= [Z_1^{(1)} \; Z_1^{(2)} \ldots Z_1^{(K)}] \; - \\ & \quad\; [Z_2^{(1)} \; Z_2^{(2)} \ldots Z_2^{(K)}] \\ &= [\Delta Z^{(1)} \; \Delta Z^{(2)} \ldots \; \Delta Z^{(K)}] \end{aligned}$$

between any two distinct code matrices in the product code $\mathcal{Z}$. At least one of the $\Delta Z^{(k)}$, say, $\Delta Z^{(k_0)}$ must be nonzero. Next, note that we can write

$$\begin{aligned} \Delta Z \Delta Z^\dagger &= [\Delta Z^{(k_0)}][\Delta Z^{(k_0)}]^\dagger & (29) \\ & \quad + \sum_{k=1, k\neq k_0}^{K} [\Delta Z^{(k)}][\Delta Z^{(k)}]^\dagger & (30) \\ &= A + B & (31) \end{aligned}$$

where $A = [\Delta Z^{(k_0)}][\Delta Z^{(k_0)}]^\dagger$ and $B = \sum_{k=1,k\neq k_0}^K [\Delta Z^{(k)}][\Delta Z^{(k)}]^\dagger$. Let

$$\mu_1^{(A)} \leq \mu_2^{(A)} \leq \cdots \leq \mu_{n_t}^{(A)} \qquad \text{and}$$

$$\mu_1^{(A+B)} \leq \mu_2^{(A+B)} \leq \cdots \leq \mu_{n_t}^{(A+B)}$$

denote the ordered eigenvalues of the Hermitian matrices $A, A+B$ respectively. Then from a theorem of Weyl (see Theorem 4.3.1 of [39]), we have that

$$\mu_i^{(A+B)} \;\geq\; \mu_i^{(A)}, \quad 1 \leq i \leq n_t.$$

As a result, we have that

$$\begin{aligned} \det([A+B]) &\geq \det(A) \\ &\stackrel{.}{\geq} \text{SNR}^{n_t - r} \end{aligned}$$

and thus the determinant condition is also met. ■

C. Simulation Results

The simulations in this section are related to the row-deletion construction of Theorem 12.

They present the performance of a rectangular $n_t = n_r = 2, T = 3$ ST code operating at 6 bpcu alongside that of the Golden code [8] operating at 4 and 12 bpcu. The code matrices in the $(n_t = 2, T = 3)$ rectangular ST code are obtained by deleting the top row in the $(n_t = 3 \times T = 3)$ CDA-based perfect [12] code. With reference to Theorem 3, this code is an admissible starting point for applying the row-deletion construction because as shown in [23], the parent $(n_t = 3 \times T = 3)$ perfect ST code satisfies the sufficiency condition in Theorem 3 relating to D-MG optimality of the parent square ST code.

We explain the structure of the rectangular code with the aid of Fig. 7.



Fig. 7. The number fields relevant to the simulated (2×3) ST code.

In Fig. 7, $\mathbb{K}$ is the subfield $\mathbb{Q}(\omega_7 + \omega_7^6)$ of $\mathbb{Q}(\omega_7)$. The extension $\mathbb{L}/\mathbb{Q}(\imath)$ is cyclic and the automorphism

$$\sigma : \sigma(\omega_7) \longrightarrow \omega_7^3, \quad \sigma(\imath) = \imath$$

is a generator of $\text{Gal}\,(\mathbb{L}/\mathbb{Q}(\imath))$. Set $\gamma = \frac{2+\imath}{1+2\imath}$ and

$$\{\beta_1, \beta_2, \beta_3\} \ = \ \{x, \sigma(x), \sigma^2(x)\}$$

where

$$x = \sum_{k=1}^{2} \tau^{3k} \left((\omega_7^4)(1-\omega_7) \prod_{k=0}^{2} (1 - \omega_7^{3^k}) \right),$$

with $\tau : \omega_7 \longrightarrow \omega_7^3$ a generator of $\text{Gal}\,(\mathbb{Q}(\omega_7)/\mathbb{Q})$. Then $\{\beta_1, \beta_2, \beta_3\}$ forms an integral basis for $\mathcal{O}_{\mathbb{L}}/\mathbb{Q}(\imath)$ and the code matrices in the (3×3) ST code are then of the form

$$X \ = \ \left[\begin{array}{ccc} l_0 & \gamma\sigma(l_2) & \gamma\sigma^2(l_1) \\ l_1 & \sigma(l_0) & \gamma\sigma^2(l_2) \\ l_2 & \sigma(l_1) & \sigma^2(l_0), \end{array} \right]$$

where

$$\ell_i \ \in \ \left\{ \sum_{j=1}^{3} f_{ij}\beta_j, \ f_{ij} \in \mathcal{A}_{\text{QAM}} \right\} \ \subseteq \ \mathcal{O}_{\mathbb{L}}.$$

This particular choice of integral basis along with the property $|\gamma| = 1$ turns out (see [12], [23]) to ensure that the collection of code matrices, after vectorization, forms a cubic constellation [12]. Moreover, each antenna element transmits the same average amount of energy in each time slot. It turns out that the resulting ST code not only satisfies the sufficiency condition identified in Theorem 3 for D-MG optimality, it also has excellent probability-of-error performance at low-moderate values of SNR.

In our simulation of the rectangular ST code, we have chosen the QAM constellation $\mathcal{A}_{\text{QAM}}$ to have size $M^2 = 4$. Thus the size of the (3×3) ST code equals 4^9. Deleting the first row does not change the size of the ST code and hence the rectangular code also has the same size and hence transmits 6 bpcu. From the row-deletion theorem, Theorem 12, this rectangular code also satisfies the sufficiency condition for D-MG optimality. From the simulation it is seen that the performance of the rectangular code also tracks channel outage.

APPENDIX I: NUMBER THEORY PRIMER

Example references for the relevant number theory include [41]–[44].



Fig. 8. Simulation of the $(n_t = n_r = 2, T = 3)$ rectangular code and comparison with outage at 6 bits per channel use (bpcu). The performance of the $(n_t = n_r = T = 2)$ Golden code (along with the relevant plots of channel outage), is also shown alongside for 4 and 12 bpcu.

A. Field Extensions

Let $\mathbb{E}, \mathbb{F}$ be fields such that $\mathbb{F} \subseteq \mathbb{E}$. Then $\mathbb{E}$ is said to be an extension field of $\mathbb{F}$. $\mathbb{E}$ is naturally a vector space over $\mathbb{F}$. The extension $\mathbb{E}/\mathbb{F}$ is said to be finite if this dimension is finite. The degree of a finite extension $\mathbb{E}/\mathbb{F}$ is the dimension of $\mathbb{E}$ as a vector space over $\mathbb{F}$ and the notation $[\mathbb{E} : \mathbb{F}]$ is used to denote the degree of the extension. If $\mathbb{E}$ is a finite extension of $\mathbb{F}$ and $\mathbb{L}$ is a finite extension of $\mathbb{E}$, then we have

$$[\mathbb{L} : \mathbb{F}] \ = \ [\mathbb{L} : \mathbb{E}][\mathbb{E} : \mathbb{F}].$$

A number field is a field that is a finite extension of the field $\mathbb{Q}$ of rational numbers. Unless otherwise specified, all fields encountered will be assumed to be number fields. Hence all fields will have characteristic zero and all extensions will be of finite degree.

If $\mathbb{E}$ is an extension of $\mathbb{F}$, then $\alpha \in \mathbb{E}$ is said to be algebraic over $\mathbb{F}$ if α is the zero of some nonzero polynomial $f(x) \in \mathbb{F}[x]$. $\mathbb{E}$ is said to be an algebraic extension of $\mathbb{F}$ if every element of $\mathbb{E}$ is algebraic over $\mathbb{F}$. Every finite extension is an algebraic extension.

Lemma 14: Let $\mathbb{S} = \mathbb{S}_1\mathbb{S}_2 \cdots \mathbb{S}_r$ be the compositum of the fields $\mathbb{S}_1$,$\mathbb{S}_2$,. . ., $\mathbb{S}_r$. If each $\mathbb{S}_i$ is an extension of $\mathbb{F}$ of degree m_i, where the m_i are pairwise relatively prime, then $\mathbb{S}$ is an extension over $\mathbb{F}$ of degree $\prod_{i=1}^{r} m_i$.

B. Algebraic Integers

An element θ in a number field $\mathbb{F}$ is said to be an algebraic integer if θ is the zero of a monic polynomial with rational integer (i.e., elements of $\mathbb{Z}$) coefficients. The set of all the algebraic integers in $\mathbb{F}$ forms a ring called the ring of integers of $\mathbb{F}$ and is denoted by $\mathcal{O}_{\mathbb{F}}$. It is also referred to as the integral closure of $\mathbb{Z}$ in $\mathbb{F}$. If $[\mathbb{L} : \mathbb{F}]$ is a finite extension of number fields, then the ring of integers $\mathcal{O}_{\mathbb{L}}$ of $\mathbb{L}$ is precisely the collection of all elements in $\mathbb{L}$ that are the zeros of monic polynomials with coefficients in $\mathcal{O}_{\mathbb{F}}$, i.e., the integral closure of $\mathcal{O}_{\mathbb{F}}$ in $\mathbb{L}$ is $\mathcal{O}_{\mathbb{L}}$.

An integral basis for an extension $\mathbb{L}/\mathbb{F}$ of number fields is a vector-space basis $\{\alpha_1, \alpha_2, \ldots, \alpha_n\}$ for $\mathbb{L}/\mathbb{F}$ satisfying the additional requirements that

- $\alpha_i \in \mathcal{O}_{\mathbb{L}}$, all i
- Every element in $\mathcal{O}_{\mathbb{L}}$ is expressible as a linear combination of elements in the basis with coefficients lying in $\mathcal{O}_{\mathbb{F}}$, i.e., $x \in \mathcal{O}_{\mathbb{L}}$ implies

$$x \;=\; \sum_{i=1}^{n} c_i \alpha_i, \quad c_i \in \mathcal{O}_{\mathbb{F}}.$$

It is known that every number field extension has an integral basis.

The term “rational integer” is often used to distinguish the elements of $\mathbb{Z}$ from those in the ring of algebraic integers of an extension field of $\mathbb{Q}$.

C. Galois Theory

The Galois group of $\mathbb{E}/\mathbb{F}$ is defined as the set of all automorphisms σ of $\mathbb{E}$ that fix every element of $\mathbb{F}$, i.e.,

$$\begin{aligned}\mathrm{Gal}(\mathbb{E}/\mathbb{F}) \;=\; & \{\sigma : \mathbb{E} \to \mathbb{E} \mid \sigma \quad \text{is an automorphism of } \mathbb{E} \\ & \text{and } \sigma(f) = f, \text{ all } f \in \mathbb{F}\ \}.\end{aligned}$$

This set forms a group under the composition operator. The size of the Galois group of the extension $\mathbb{E}/\mathbb{F}$ is always $\leq [\mathbb{E} : \mathbb{F}]$. The extension is said to be Galois if equality holds. An Abelian (cyclic) extension $\mathbb{E}/\mathbb{F}$ is a Galois extension in which the Galois group is Abelian (cyclic).

We digress briefly to state a lemma related to cyclic groups.

Lemma 15: Let G be a cyclic group of size g and H the unique subgroup of size h with $h|g$. Then G/H is cyclic of size g/h.

Proof: Let ψ be the homomorphism from G onto $\psi(G)$ defined by

$$\psi(x) = x^h \ , \ x \in G \ .$$

Clearly, $\psi(G)$ is a cyclic subgroup of G of order g/h. The kernel K_ψ of ψ is the set of all elements of G whose order divides h. It follows that the kernel is a cyclic subgroup of size h and since H is the unique subgroup of this size, it follows that

$$K_\psi \;=\; H \ .$$

It follows that $G/H \;\cong\; \psi(G)$ and is therefore cyclic. ■

A subfield $\mathbb{E} \supset \mathbb{F}$ of $\mathbb{L}$ is said to be fixed (elementwise) by a subgroup H of $\mathrm{Gal}(\mathbb{L}/\mathbb{F})$ if

$$\sigma(x) \;=\; x \quad \text{for all} \quad x \in \mathbb{E} \quad \text{and all} \quad \sigma \in H.$$

Proposition 16: (Fundamental Theorem of Galois Theory) Let $\mathbb{K}_1$ be a finite Galois extension of $\mathbb{F}$. Then there is a one-one correspondence between the subfields $\mathbb{K}$ of $\mathbb{K}_1$ containing $\mathbb{F}$ and subgroups H of $G = \mathrm{Gal}(\mathbb{K}_1/\mathbb{F})$. The correspondence maps a subgroup H of G to the largest subfield $\mathbb{K}$ of $\mathbb{K}_1$ fixed by the subgroup and subfields $\mathbb{K}$ of $\mathbb{K}_1$ containing $\mathbb{F}$ to the largest subgroup of G fixing the subfield. Moreover, under this correspondence,

- $\mathrm{Gal}(\mathbb{K}_1/\mathbb{K}) \;=\; H$
- $\mathrm{Gal}(\mathbb{K}/\mathbb{F}) \;\cong\; G/H$



Fig. 9. The Fundamental Theorem of Galois Theory

Lemma 17: Let $\mathbb{S} = \mathbb{S}_1\mathbb{S}_2 \cdots \mathbb{S}_r$ be the compositum of the fields $\mathbb{S}_1$,$\mathbb{S}_2$,. . ., $\mathbb{S}_r$. If each $\mathbb{S}_i$ is a cyclic Galois extension over $\mathbb{F}$ of degree n_i, where the n_i are pairwise relatively prime, then $\mathbb{S}$ is a cyclic Galois extension over $\mathbb{F}$ of degree $\prod_{i=1}^{r} n_i$.

Proof: Consider the compositum $\mathbb{S} = \mathbb{S}_1\mathbb{S}_2 \ldots \mathbb{S}_r$. Each $\mathbb{S}_i/\mathbb{F}$ is a cyclic Galois extension of order n_i such that $(n_i, n_j) = 1 \ \forall \ i \neq j$. Thus,

$$\begin{aligned}\mathbb{S}_i \cap \mathbb{S}_j \;&=\; \mathbb{F} \ \forall \ i \neq j \\ \Rightarrow \mathrm{Gal}(\mathbb{S}/\mathbb{F}) \;&=\; \mathrm{Gal}(\mathbb{S}_1/\mathbb{F}) \times \cdots \times \mathrm{Gal}(\mathbb{S}_r/\mathbb{F}).\end{aligned}$$

It follows that $\mathbb{S}/\mathbb{F}$ is cyclic of degree n. ■

D. Prime-Ideal Decomposition in Number-Field Extensions

The integral closure $\mathcal{O}_{\mathbb{F}}$ of $\mathbb{Z}$ in a number field $\mathbb{F}$ is a Dedekind domain and hence every prime ideal of $\mathcal{O}_{\mathbb{F}}$ is a maximal ideal. To distinguish primes in $\mathbb{Z}$ from prime ideals of the ring of integers $\mathcal{O}_{\mathbb{F}}$ of a number field $\mathbb{F}$, the term “rational prime” is often used to describe prime elements of $\mathbb{Z}$. Every ideal I of $\mathcal{O}_{\mathbb{F}}$ has a unique factorization as the products of powers of prime ideals. Let $\mathbb{E}$ be a finite Galois extension of $\mathbb{F}$ and let $\mathcal{O}_{\mathbb{E}}$ denote the ring of integers of $\mathbb{E}$. If $\mathfrak{p}$ is a prime ideal of $\mathcal{O}_{\mathbb{F}}$, then the ideal $\mathfrak{p}\mathcal{O}_{\mathbb{E}}$ of $\mathcal{O}_{\mathbb{E}}$ has a unique factorization of the form

$$\mathfrak{p} \ \mathcal{O}_{\mathbb{E}} \;=\; \prod_{i=1}^{g} \beta_i^{e}, \tag{32}$$

for distinct prime ideals β_i of $\mathcal{O}_{\mathbb{E}}$. The ideal $\mathfrak{p}$ can be recovered from any of the β_i via

$$\mathfrak{p} \;=\; \beta_i \cap \mathcal{O}_{\mathbb{F}}.$$

The exponent e is called the ramification index of β_i over $\mathfrak{p}$ and written $e(\beta_i/\mathfrak{p})$. This number is the same for all β_i. We will also loosely refer to $e(\beta_i/\mathfrak{p})$ as the ramification index of $\mathfrak{p}$ or the ramification index of β_i. One may naturally regard the field $\mathcal{O}_{\mathbb{E}}/\beta_i$ as an extension of the field $\mathcal{O}_{\mathbb{F}}/\mathfrak{p}$ and the degree of this extension is called the relative degree of β_i over $\mathfrak{p}$ and written $f(\beta_i/\mathfrak{p})$. This relative degree is also the same for all i. The decomposition group $G_{\mathfrak{p}}$ of the ideal $\mathfrak{p}$ of $\mathcal{O}_{\mathbb{F}}$ is the largest subgroup of Gal$(\mathbb{E}/\mathbb{F})$ which fixes $\mathfrak{p}$, i.e.,

$$G_{\mathfrak{p}} \;=\; \{\sigma \in \text{Gal}(\mathbb{E}/\mathbb{F}) \mid \quad \sigma(\nu) \in \mathfrak{p} \text{ whenever } \nu \in \mathfrak{p}\}.$$

It turns out that the index

$$\mid \text{Gal}(\mathbb{E}/\mathbb{F})/G_{\mathfrak{p}} \mid$$

of the decomposition group equals the integer $g := g(\beta_i/\mathfrak{p})$ appearing in the factorization of $\mathfrak{p}\mathcal{O}_{\mathbb{E}}$ in (32). Moreover,

$$e(\beta_i/\mathfrak{p})\ f(\beta_i/\mathfrak{p})\ g(\beta_i/\mathfrak{p}) \;=\; [\mathbb{E}:\mathbb{F}] \;= n\ . \tag{33}$$

The prime ideal $\mathfrak{p}$ is said to be inert if

$$f(\beta_i/\mathfrak{p}) \;=\; [\mathbb{E}:\mathbb{F}] \;= n$$

in which case, $e(\beta_i/\mathfrak{p}) = g(\beta_i/\mathfrak{p}) = 1$.

Let $\mathbb{L}$ be a Galois extension of $\mathbb{E}$. If

$$\mathcal{O}_{\mathbb{L}}\beta_i \;=\; \prod_{j=1}^{g'} \gamma_j^{e'}$$

is the unique factorization of the ideal $\mathcal{O}_{\mathbb{L}}\beta_i$ in $\mathcal{O}_{\mathbb{L}}$ in terms of prime ideals γ_j, then we have that

$$\begin{aligned} e(\gamma_j/\mathfrak{p}) \;:=\; e' \;&=\; e(\gamma_j/\beta_i)e(\beta_i/\mathfrak{p}) && (34)\\ f(\gamma_j/\mathfrak{p}) \;&=\; f(\gamma_j/\beta_i)f(\beta_i/\mathfrak{p}) && (35)\\ g(\gamma_j/\mathfrak{p}) \;:=\; g' \;&=\; g(\gamma_j/\beta_i)g(\beta_i/\mathfrak{p}) && (36)\end{aligned}$$

E. Cyclotomic Extensions

Cyclotomic extensions are extensions of the rationals of the form $\mathbb{Q}(\omega_m)/\mathbb{Q}$ where

$$\omega_m = \exp\left(\frac{\imath 2\pi}{m}\right)$$

for some integer $m \geq 3$. The degree of this extension equals $\phi(m)$ where ϕ is Euler's totient function. Such extensions are of interest here as by a theorem of Kronecker-Weber [42], every Abelian extension (and therefore every cyclic extension) of $\mathbb{Q}$ is contained in a cyclotomic extension.

For $m \geq 3$, let $\mathbb{Z}_m$ denote the set of integers modulo m and let $\mathbb{Z}_m^*$ be the multiplicative group formed by the elements $a \in \mathbb{Z}_m$ such that $(a, m) = 1$. The following facts will be useful in our study of cyclotomic extensions:

Lemma 18: [44] The Galois group $\text{Gal}(\mathbb{Q}(\omega_m)/\mathbb{Q}) \cong \mathbb{Z}_m^*$.

Lemma 19: [44] $\mathbb{Z}_m^*$ is a cyclic group iff $m = 2, 4, p^e, 2p^e$ where $e \geq 1$ and p is an odd prime.

Lemma 20: [44] For $e \geq 3$,

$$\mathbb{Z}_{2^e}^* \;\cong\; \mathbb{Z}_2 \times \mathbb{Z}_{2^{e-2}}.$$

From Lemmas 18 and 19 it follows that:

Corollary 21: Let $m \geq 2$ be an integer. Then the Galois extension $\mathbb{Q}(\omega_m)/\mathbb{Q}$ is cyclic iff $m = 2, 4, p^e, 2p^e$.

Lemma 22: The ring of algebraic integers of a cyclotomic field $\mathbb{Q}(\omega_m)$ is the ring $\mathbb{Z}[\omega_m]$, i.e., the algebraic closure of $\mathbb{Z}$ in $\mathbb{Q}(\omega_m)$ is $\mathbb{Z}[\omega_m]$.

Lemma 23: Let p be prime and $m \geq 1$. The only rational prime q for which the prime ideal $q\mathbb{Z}[\omega_{p^m}]$ is ramified (i.e., has ramification index $e > 1$) in $\mathbb{Q}(\omega_{p^m})/\mathbb{Q}$ is the prime p itself.

Lemma 24: [44] Let p be prime, m an integer ≥ 1 and let $\omega = \exp\left(\frac{\imath 2\pi}{p^m}\right)$. Let q be any prime number distinct from p, let $f \geq 1$ be the smallest integer such that $q^f \equiv 1 \pmod{p^m}$ and let $g = \phi(p^m)/f$. Then $q\mathbb{Z}(\omega_{p^m}) \;=\; \beta_1 \cdots \beta_g$ where $\beta_1, \cdots, \beta_g$ are distinct prime ideals of $\mathbb{Z}(\omega_{p^m})$. In particular, if the order of $q \pmod{p^m} = \phi(p^m)$, then $f = \phi(p^m)$, $g = 1$, so that the prime ideal $q\mathbb{Z}(\omega_{p^m})$ remains inert in $\mathbb{Q}(\omega_{p^m})/\mathbb{Q}$.

APPENDIX II: REPLACING THE QAM CONSTELLATION WITH A HEX CONSTELLATION

a) HEX Constellation: For $M \geq 2$, M even, we define

$$\mathcal{A}_{\text{HEX}} \;=\; \{a + \omega_3 b \mid \ |a|, |b| \leq (M-1),\ a, b \ \text{ odd}\},$$

and will term the resulting constellation the HEX constellation, (see [12]). For any particular value of M, a slightly different collection of points from the lattice $\{a + \omega_3 b\}$ may be preferable from the point of view of improving the shaping gain, but for the purposes of constructing codes that are D-MG optimal, this constellation will suffice. Note that as with the M^2-QAM constellation, we have

$$\begin{aligned} x \in \mathcal{A}_{\text{HEX}} \;&\Rightarrow\; |x|^2 \leq 2M^2 \quad \text{and}\\ \mathbb{E}(|x|^2) \;&=\; \frac{M^2-1}{3} \end{aligned} \tag{37}$$

assuming that every constellation point is chosen at random.

b) Endowing the NVD Property: The discussion in Section II-D carries over to the HEX case if one replaces the ring $\mathbb{Z}[\imath]$ with the ring $\mathbb{Z}[\omega_3]$ of Eisenstein integers since every nonzero element $x \in \mathbb{Z}[\omega_3]$ has $|x| \geq 1$.

c) Proof of D-MG Optimality: It follows from (37) that the proof of optimality remains unchanged in the case of the HEX constellation.

d) Constructing D-MG Optimal CDA Codes: An examination of Section III shows that the crucial ingredient needed for constructing a D-MG optimal CDA-based ST code over the HEX constellation is the construction of a cyclic field extension $\mathbb{L}/\mathbb{Q}(\omega_3)$ such that the corresponding ring extension $\mathcal{O}_{\mathbb{L}}/\mathbb{Z}[\omega_3]$ contains a prime ideal that remains inert.

We provide constructions for the case $n \neq 0 \pmod 4$. Let p^e be the smallest power of an odd prime p such that $n|\phi(p^e)$. From Lemma 6, we know that $\mathbb{Q}(\omega_{p^e})$ contains a subfield $\mathbb{K}$ that is a cyclic extension of $\mathbb{Q}$ of degree n_1. Let $\mathbb{M}$ be the



Fig. 10. The number fields that appear in the HEX constellation construction for $n \neq 0 \pmod 4$.

compositum of $\mathbb{Q}(\omega_3)$ and $\mathbb{K}$ and $\mathbb{L}$ be the compositum of $\mathbb{Q}(\omega_{12})$ and $\mathbb{M}$ (see Fig. 10).

Consider the extension $\mathbb{Q}(\omega_{12})/\mathbb{Q}(\omega_3)$ (Fig. 11). This extension is cyclic of degree 2 and the Galois group is cyclic having generator $\sigma : \omega_{12} \to \omega_{12}^7$.



Fig. 11. This figure helps identify an inert prime ideal in the extension $\mathbb{Q}(\omega_{12})/\mathbb{Q}(\omega_3)$.

Let q be a rational prime satisfying

$$q = \begin{cases} \rho & \pmod{p^e} \\ 1 & \pmod 3 \\ 3 & \pmod 4. \end{cases}$$

Then the ideal $q\mathbb{Z}$ splits into the product of two prime ideals β_1, β_2 in $\mathbb{Q}(\omega_3)/\mathbb{Q}$ since $q = 1 \pmod 3$. On the other hand, $q\mathbb{Z}$ is inert in $\mathbb{Q}(\imath)/\mathbb{Q}$ since $q = 3 \pmod 4$. Hence it follows that each of the prime ideals β_i is inert in $\mathbb{Q}(\omega_{12})/\mathbb{Q}(\omega_3)$. Since $q = \rho \pmod{p^e}$, it follows that the ideal $q\mathbb{Z}$ is inert in $\mathbb{K}/\mathbb{Q}$, hence the ideals β_i remain inert in $\mathbb{M}/\mathbb{Q}(\omega_3)$, therefore inert in $\mathbb{L}/\mathbb{Q}(\omega_{12})$ and as a consequence of their inertness in $\mathbb{Q}(\omega_{12})/\mathbb{Q}(\omega_3)$, inert in $\mathbb{L}/\mathbb{Q}(\omega_3)$ as well.

Then $\mathbb{M}/\mathbb{Q}(\omega_3)$ and $\mathbb{L}/\mathbb{Q}(\omega_3)$ are the desired cyclic extensions of $\mathbb{Q}(\omega_3)$ for the cases $e_0 = 0, e_0 = 1$ respectively. Note that in either extension, the ideals β_i are inert.

APPENDIX III: MISCELLANEOUS PROOFS

A. Proof of Lemma 1 – Determinant Lies in the Center

Proof: We have

$$\begin{aligned} (\sum_{i=0}^{n-1} z^i \ell_i) \cdot z &= (\sum_{i=0}^{n-1} z^{i+1} \sigma(\ell_i)) , && (38) \\ &= z(\sum_{i=0}^{n-1} z^i \sigma(\ell_i)) , && (39) \\ \therefore z^{-1}(\sum_{i=0}^{n-1} z^i \ell_i) \cdot z &= \sum_{i=0}^{n-1} z^i \sigma(\ell_i). && (40) \end{aligned}$$

It follows as a result, that the left-regular representations of

$$\sum_{i=0}^{n-1} z^i \ell_i \text{ and of } \sum_{i=0}^{n-1} z^i \sigma(\ell_i)$$

are similar and therefore have the same determinant. However, from inspection of (7), it follows that the left-regular representation of $\sum_{i=0}^{n-1} z^i \sigma(\ell_i)$ equals $\sigma(A)$ where A is the left regular representation of $\sum_{i=0}^{n-1} z^i \ell_i$. It follows that A and $\sigma(A)$ are similar and hence have the same determinant, i.e.,

$$\begin{aligned} \det(\sigma(A)) &= \det(A) \\ \text{i.e.,} \quad \sigma(\det(A)) &= \det(A), \end{aligned}$$

so that $\det(A) \in \mathbb{F}$. ■

B. Proof of (11) – Mismatched Eigenvalue Bound

From (10), we have

$$\frac{d_E^2(\Delta X, H)}{\theta^2} = \text{Tr}(H \Delta X \Delta X^\dagger H^\dagger).$$

Using $\text{Tr}(AB) = \text{Tr}(BA)$ and the eigenvector decompositions $\Delta X \Delta X^\dagger = V L V^\dagger$ and $H^\dagger H = U^\dagger \Lambda U$, U, V unitary, Λ, L diagonal, this can be rewritten in the form,

$$\begin{aligned} \frac{d_E^2(\Delta X, H)}{\theta^2} &= \text{Tr}(V^\dagger U^\dagger \Lambda U V L) \\ &= \sum_{i,j=1}^{n_t} \lambda_i l_j |d_{ij}|^2, && (41) \\ & \qquad (D = [d_{ij}] = UV, \text{ also unitary}). && (42) \end{aligned}$$

Let $a_{ij} = |d_{ij}|^2$. Then,

$$\sum_i a_{ij} = \sum_j a_{ij} = 1 \qquad (43)$$

The RHS of (41) is equal to the sum of the elements of the matrix

$$\begin{bmatrix} \lambda_1 l_1 a_{11} & \lambda_1 l_2 a_{12} & \cdots & \lambda_1 l_n a_{1n_t} \\ \lambda_2 l_1 a_{21} & \lambda_2 l_2 a_{22} & \cdots & \lambda_2 l_n a_{2n_t} \\ \vdots & \vdots & \ddots & \vdots \\ \lambda_{n_t} l_1 a_{n_t 1} & \lambda_{n_t} l_2 a_{n_t 2} & \cdots & \lambda_{n_t} l_{n_t} a_{n_t n_t} \end{bmatrix} \qquad (44)$$

We want to show that setting

$$a_{ij} = \begin{cases} 1, & i = j \\ 0, & \text{otherwise} \end{cases} ,$$

minimizes this sum subject to (43). Consider any valid assignment of the $\{a_{i,j}\}$. If $a_{11} \neq 1$, then, at least two entries, one each in the first row and first column are non-zero, say $a_{p1} = \kappa_1$ and $a_{1q} = \kappa_2$ (where, neither p nor q is 1). Define $\kappa = \min\{\kappa_1, \kappa_2\}$. Consider now the matrix below, obtained by shifting "weights" κ from a_{p1} and a_{1q} to a_{11} and a_{pq} respectively while satisfying (43) as shown below.

$$\begin{bmatrix} l_1\lambda_1(a_{11}+\kappa) & \cdots & l_q\lambda_1(a_{1q}-\kappa) & \cdots & l_{n_t}\lambda_1 a_{1n_t} \\ l_1\lambda_2 a_{21} & \cdots & l_q\lambda_2 a_{2q} & \cdots & l_{n_t}\lambda_2 a_{2n_t} \\ \vdots & \ddots & \vdots & \ddots & \vdots \\ l_1\lambda_p(a_{p1}-\kappa) & \cdots & l_q\lambda_p(a_{pq}+\kappa) & \cdots & l_{n_t}\lambda_p a_{pn_t} \\ \vdots & \ddots & \vdots & \ddots & \vdots \\ l_1\lambda_{n_t} a_{n_t1} & \cdots & l_q\lambda_{n_t} a_{n_tq} & \cdots & l_{n_t}\lambda_{n_t} a_{n_tn_t} \end{bmatrix} \tag{45}$$

The difference between the sums of the entries of the matrices in (44) and (45) equals

$$\begin{aligned} & \kappa\lambda_1 l_1 + \kappa\lambda_p l_q - \kappa\lambda_p l_1 - \kappa\lambda_1 l_q \\ = \; & \kappa \underbrace{[\lambda_1 - \lambda_p]}_{positive} \underbrace{[l_1 - l_q]}_{negative} \text{ is negative} \end{aligned}$$

where we have used (9). Thus we see that shifting weights towards the diagonal entry a_{11} results in a reduction in $d_E^2(\Delta X, H)$. Repeated application of this procedure gives us $a_{11} = 1$ and $a_{1i}, a_{i1} = 0$ for $i \neq 1$. Repeating this procedure with the first row and column removed leads us to setting $a_{22} = 1$ as well and so on, leading to $a_{ii} = 1$, all i. □

ACKNOWLEDGEMENT

Thanks are due to B. Sethuraman for the particular proof of Lemma 1 appearing in the paper as well as for drawing our attention to the results on the eigenvalues of submatrices of Hermitian matrices contained in [39]. Thanks are also due to B. Sundar Rajan and E. Viterbo for making available preprints of their recent work.

REFERENCES

[1] L. Zheng and D. Tse, "Diversity and multiplexing: A fundamental tradeoff in multiple-antenna channels," *IEEE Trans. Info. Theory*, vol. 49, no. 5, pp. 1073-1096, May 2003.

[2] I. E. Telatar, "Capacity of multi-antenna Gaussian channels," *Europ. Trans. Telecomm.*, vol. 10, no. 6, pp. 585–595, Nov.-Dec. 1999.

[3] G. J. Foschini, "Layered space-time architecture for wireless communication in a fading environment when using multi-element antennas," *Bell Labs Tech. J.*, vol. 1, no. 2, pp. 41-59, 1996.

[4] R. Heath and A. Paulraj, "Switching between mulitplexing and diversity based on constellation distance," in *Proc. Allerton Conf. Comm., Control and Computing*, Oct. 2000.

[5] H. Yao, G.W. Wornell, "Achieving the full MIMO diversity-multiplexing frontier with rotation based space-time codes," in *Proc. Allerton Conf. Comm., Control and Computing*, Oct. 2003.

[6] H. Yao, "Efficient signal, code, and receiver designs for MIMO communication systems," Ph.D. thesis, MIT, 2003.

[7] P. Dayal and M. K. Varanasi,"An optimal two transmit antenna space-time code and its stacked extension," *Proc. Asilomar Conf. on Signals, Systems and Computers*, Monterey, CA, Nov. 2003.

[8] J.-C. Belfiore, G. Rekaya and E.Viterbo, "The Golden code: a 2×2 full-rate space-time code with non-vanishing determinants," *IEEE Trans. Inform. Theory*, vol.51, No. 4, April 2005, pp. 1432-1436.

[9] Petros Elia, P. Vijay Kumar, Sameer Pawar, K. Raj Kumar, B. Sundar Rajan and Hsiao-feng (Francis) Lu, "Diversity-multiplexing tradeoff analysis of a few algebraic space-time constructions, " in *Proc. Allerton Conf. Comm., Control and Computing*, Oct. 2004.

[10] Huiyong Liao, Haiquan Wang and Xiang-Gen Xia "Some designs and diversity product upper bounds for lattice based diagonal and full rate space-time block codes," preprint, September 29, 2004.

[11] G. Rekaya, J.-C. Belfiore and E.Viterbo, "Algebraic 3×3, 4×4 and 6×6 space-time codes with non-vanishing determinants," *Int. Symp. Inform. Th and its Applns.*, Parma, Italy, October 10-13, 2004, p. 325-329.

[12] F. Oggier, G. Rekaya, J -C. Belfiore and E. Viterbo, "Perfect space time block codes," Submitted to *IEEE Trans. Inform. Theory*, Sep. 2004.

[13] M. O. Damen, A. Tewfik, and J.-C. Belfiore, "A construction of a space-time code based on number theory," *IEEE Trans. Inform. Theory*, vol. 48, no. 3, pp. 753–760, Mar. 2002.

[14] H. El Gamal and M.O. Damen,"Universal space-time coding,"*IEEE Trans. Inform. Theory*, Vol. 49, No.5, pp. 1097-1119, May 2003.

[15] H. El Gamal, G. Caire and M.O. Damen,"Lattice coding and decoding achieve the optimal diversity-multilpexing tradeoff of MIMO channels,"*IEEE Trans. Inform. Theory*, vol. 50, pp. 968-985, June 2004.

[16] H.A.Loeliger, "Averaging arguments for lattices and linear codes, "*IEEE Trans. Inform. Theory*, vol. 43, pp.1767-1773, Nov.1997

[17] B. A. Sethuraman and B.Sundar Rajan, "Full-rank, full-rate STBCs from division algebras," *Proc. IEEE Inform. Theory Workshop*, pp. 69-72, Oct. 20 - 25, 2002, Bangalore, India.

[18] B. A. Sethuraman and B.Sundar Rajan, "An algebraic description of orthogonal designs and the uniqueness of the Alamouti code," *Proc. IEEE Global Telecom. Conf.*, Taipei, pp. 1088-1092, 2002.

[19] V. Shashidhar, B.Sundar Rajan and B.A.Sethuraman, "STBCs using capacity achieving designs from cyclic division algebras,"*Proc. IEEE Global Telecomm. Conf.*, 1-5 Dec., San Francisco, 2003, Vol.4, pp.1957-1962.

[20] B. A. Sethuraman, B. Sundar Rajan and V. Shashidhar, "Full-diversity, high-rate, space-time block codes from division algebras," *IEEE Trans. Info. Theory*, vol. 49, pp. 2596-2616, Oct. 2003.

[21] S. Alamouti,"A transmitter diversity scheme for wireless communications, "*IEEE J. Select. Areas Commun.*, vol. 16, pp. 1451-1458, Oct 1998.

[22] J.-C. Belfiore and G. Rekaya,"Quaternionic lattices for space-time coding," in *Proc. IEEE Inform. Theory Workshop.*, Paris, 31 March - 4 April 2003.

[23] Petros Elia, Bharath Sethuraman and P. Vijay Kumar, "Perect space-time codes with minimum and non-minimum delay for any number of antennas," preprint, submited to arXiv:cs.IT/0512023, v1, 6 Dec 2005.

[24] Kiran.T. and B.Sundar Rajan, "STBC-schemes with non-vanishing determinant for certain number of transmit antennas," *IEEE Trans. Inform. Theory*, vol. 51, no. 8, pp.2984-2992, Aug. 2005.

[25] S. Tavildar and P. Viswanath,"Permutation codes: achieveing the diversity-multiplexing tradeoff," *Proc. IEEE Int. Symp. Inform. Th*, Chicago, pp. 98, June 27-July 2, 2004.

[26] S. Tavildar and P. Viswanath, "Permutation codes for the parallel fading channel: Achieving the diversity-multiplexing tradeoff," *Proc. CISS-2004*, Feb. 2004.

[27] S. Tavildar and P. Viswanath, "Approximately universal codes over slow fading channels," *Submitted to IEEE Trans. Info. Theory*, Feb. 2005.

[28] David Tse and Pramod Viswanath, *Fundamentals of Wireless Communication*, Cambridge University Press, May 2005.

[29] P. Vijay Kumar, Petros Elia, Hsiao-feng (Francis) Lu, Sameer Pawar and K. Raj Kumar, "On the decoding and diversity-multiplexing gain tradeoff of a recent multilevel construction of space-time codes, " *Proc. IEEE Int. Symp. Inform. Theory*, pp. 128, June 27 - July 2, 2004, Chicago.

[30] V. Shashidhar, B.Sundar Rajan and P. Vijay Kumar, "STBCs with optimal diversity-multiplexing tradeoff for 2,3 and 4 transmit antennas," *Proc. IEEE Int. Symp. Inform. Theory*, pp. 125, June 27 - July 2, 2004, Chicago.

[31] V. Shashidhar, B. Sundar Rajan and B. A. Sethuraman, "Information-lossless space time block codes from crossed-product algebras," *IEEE Trans. Inform. Theory*, to appear.

[32] Kiran. T and B.Sundar Rajan, "High-rate Full-rank Space-Time Block Codes from Cayley Algebra," *Proc. of International Conference on Signal Processing and Communications* (SPCOM 2004), Dec. 11-14, 2004, IISc Bangalore.

[33] Hsiao-feng Lu and P. Vijay Kumar, "A Unified Construction of Space-Time Codes with Optimal Rate-Diversity Tradeoff," *IEEE Trans. Inform. Theory*, May 2005.

[34] Hsiao-feng Lu and P. Vijay Kumar, "Generalized unified construction of space-time codes with optimal rate-diversity tradeoff", *Proc. IEEE Int. Symp. Inform. Theory*, pp. 95, June 27 - July 2, 2004, Chicago.

[35] A. R. Hammons, Space-time codes that achieve the rate-diversity tradeoff for certain AM-PSK modulations, submitted to *IEEE Trans. on Inform. Theory*, Mar. 2004.

[36] H. Lu,"Generalized super-unified constructions for space-time codes and their subset-subcodes that achieve rate- diversity tradeoff," *Submitted to IEEE Trans. Info. Theory,* June 2004.

[37] A. A. Albert, *Structure of Algebras*, Coll. Publ., Vol. 24, Amer. Math. Soc., Providence, R. I., 1961.

[38] W. Scharlau, *Quadratic & Hermitian Forms (Grundlehren Der Mathematischen Wissenchaften Series, Vol 270)* , Springer-Verlag, 1984.

[39] R. A. Horn and C. R. Johnson, *Matrix Analysis*. Cambridge, UK: Cambridge University Press, 1985.

[40] Paul J. McCarthy, *Algebraic extensions of fields*, New York: Dover Publications, 1991.

[41] D. A. *Marcus, Number Fields* (Universitext), Springer Verlag, New York, 1977.

[42] Robert L. Long, *Algebraic Number Theory*, Marcel Dekker, New York, 1977.

[43] S. Lang, *Algebraic Number Theory*, 2nd ed. New York: Springer-Verlag: Graduate texts in mathematics, 1994.

[44] Paulo Ribenboim, *Classical Theory of Algebraic Numbers*, New York: Springer-Verlag: Universitext, 2001.

[45] C. Köse and R. D. Wesel, "Universal space-time trellis codes," *IEEE Trans. Inform. Theory*, vol. 49, no. 10, pp. 2717-2727, Oct. 2003.

[46] A. R. Calderbank, S. Diggavi, S. Das and N. Al-Dhahir,"Construction and analysis of a new 4×4 orthogonal space-time block code," *Proc. of IEEE International Symposium on Information Theory*, Chicago, June 27- July 2, 2004, p.309.

[47] B. Hassibi and B. Hochwald, "High-rate codes that are linear in space and time," *IEEE Trans. Inform. Theory*, vol. 48, pp. 1804-824, July 2002.

[48] M. O. Damen, A. Chkeif, and J.-C. Belfiore, "Lattice codes decoder for space-time codes," *IEEE Commun. Lett*, vol. 4, pp. 161 - 163, May 2000.

[49] M. O. Damen, K. Abed-Meraim, and J.-C. Belfiore, "A generalized sphere decoder for asymmetrical space-time communication architecture," *Electron. Lett.*, p. 166, Jan. 2000.